

SNMPv2 MIB & TRAP

VC-MDx Recorder

Version 2207

VoiceCollect GmbH | Justus-von-Liebig-Str. 5 | 61352 Bad Homburg | Germany

Table of Contens

1	Docu	ument History4
2	Intro	duction4
3	Conf	figure SNMP on VC-MDx Recorder5
	3.1	Enable SNMP on VC-MDx Configurator5
	3.2	Open VC-MDx Recorder application and ensure for the version is version 14.4.x.x to run SNMP service
	3.3	Click SNMP service icon7
	3.4	A window of SNMP Settings displayed then click Save8
	3.5	Right click on column Managers (for traps sending) and select Add9
	3.6	Window Remote Entity Configuration10
	3.7	Insert IP Address of PC receiver to receive SNMP traps and tick Version 2 then OK
	3.8	IP Address of PC receiver to receive SNMP traps has been Add then Save.12
4	Оре	rating of SNMP MIB13
	4.1	Open "ManageEngine MibBrowser" application
	4.2	Select Edit and choose Settings. Choose SNMP Version tick v2c then OK.13
	4.3	From menu bar "File" select "Load MIB", then select a MIB file14
	4.4	The list of SNMP OID (Object ID) displayed15
	4.5	Right click on a SNMP OID then select "GET" or "GETNEXT" to obtain theselectedSNMP data(s) from VC-MDx Recorder.15
	4.6	Right click on a SNMP OID folder then select "SNMPWALK" to obtain the all SNMP data(s) from VC-MDx Recorder
5	Оре	rating of SNMP TRAP17
	5.1	Open "ManageEngine MibBrowser" and click "View" on menu bar and select "Trap Viewer"
	5.2	Insert IP address of VC-MDx Recorder machine on "TrapParser" then click Add and Start
	5.3	The window "TrapViewer" is running18
	5.4	The "TrapViewer" is getting a Trap data from VC-MDx Recorder19

SNMP V2

	5.5	Double click that Trap data then a window "Trap Details" displayed for the message
6	SNM	P TRAP Samples21
	6.1	VC-MDx Workstation: Connected21
	6.2	VC-MDx Workstation : disconnected22
	6.3	VDS Connected23
	6.4	User logged off/locked successful from the recorder24
	6.5	User logged on/unlocked failed on the recorder25
	6.6	User logged on/unlocked successful on the recorder
	6.7	Recording Started28
	6.8	VC-MDx Administrator : Connected29
	6.9	VC-MDx Administrator : disconnected
	6.10	Channels inactivity (Restored Channel)
	6.11	Recording started/stopped event (Stopped Channel)
	6.12	Recording started/stopped event (Started Channel)
	6.13	Network client connected/disconnected (VDS Sip Passive service started)34
	6.14	System warnings (VDS Sip Passive service stopped)

1 Document History

Version	Date	Author	Changed
01.00	2022-07-25	MR / PE	Initial Version based on 14.4.x.x

2 Introduction

This document informs the SNMPv2 MIB and TRAP setting and information in Windows against an application of VC-MDx Recorder intended to monitor the recording function. The version of VC-MDx Recorder application to run SNMP MIB and TRAP must be in version 14.4.x.x.

3 Configure SNMP on VC-MDx Recorder

3.1 Enable SNMP on VC-MDx Configurator.

			Buffer Configuration
Coding Law	External Contacts	Deck recording mode	Channels Allocation
A Law	C Opener	Automatic	General Settings
C μLaw	C Closer	С Сору	😴 Users
Computer Aided Dispatch —		Serial number	Debekara Settia
Enable CAD C VCP	C VCP XML C ILP C LLP		Database Setting
Enab	le play on VCP	WIN OS Language	NAS Settings
IP Address	Port 0	Run as Windows Service	AUX Data Setting
		-SNMP	Equalization Setting
			Restricted OS Acc
FTP Settings			
Ling and solution and			-
URI:			
URI: User name:			
URI: User name: Password:			ቃ ASA-4 Settings
URI: User name: Password: No of tries: 0	Retrial delay timer:	10 minutes	,ቃ ASA-4 Settings Save default settin
URI:	Retrial delay timer:	10 minutes	 ASA-4 Settings Save default settin Load default settin
URI: User name: Password: No of tries: 0 SARP Enable SARP SARP IP	Retrial delay timer: UDP Port 8660	10 minutes	
URI: User name: Password: Password: O No of tries: O SARP SARP SARP IP	Retrial delay timer: UDP Port 8660	10 minutes	 ✓ ASA-4 Settings Save default settin Load default settin ✓ OK ✓ Apply

3.2 Open VC-MDx Recorder application and ensure for the version is version 14.4.x.x to run SNMP service.

SRV3	3 - VC-MDx R	ecorder - IR Buffe	er Records - Super													- [X I
Lock 1	<u>V</u> iew <u>R</u> eco	ords <u>S</u> ettings	<u>S</u> ervice <u>H</u>	<u>l</u> elp													
08	78	🕈 🔎		00		Q 😹 🌘	2	_			_	-			2: 1	33	
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca	Marked	Direction	Start T	ìme	Stop Time	Duration	Disc Lab	
Closed	4977	3	channel 3				No			No		17/06	/2022 1:57:19	17/06/2022 2:00:22	00:03:02		
Closed	4976	1	channel_1				No			Yes		17/06	/2022 1:54:44	17/06/2022 1:55:11	00:00:27		
Closed	4975	1	channel_1				No			Yes		17/06	/2022 1:53:22	17/06/2022 1:54:18	00:00:56		
/ Closed	4974	2	channel_2				No			Yes		16/06	/2022 6:32:13	16/06/2022 6:32:29	00:00:16		
Closed 2	4973	1	channel_1				No			Yes		16/06	/2022 6:28:58	16/06/2022 6:29:53	00:00:55		
Closed 2	4972	1	channel_1				No			Yes		16/06	/2022 6:01:40	16/06/2022 6:02:06	00:00:26		
Closed	4971	2	channel_2				No			No		14/06	/2022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed 2	4970	1	channel_1				No			No		14/06	/2022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed	4964	2	channel_2				No			No		14/06	/2022 6:16:52	14/06/2022 6:16:59	00:00:07		<u></u>
Closed 2	4963	1	channel_1				No			No		14/06	/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed 🖉	4969	2	channel_2			13/06	No			No		13/06	/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4968	1	channel_1			13/06	No			No		13/06	/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4967	5	channel_5				No			No		13/06	2022 6:48:23	13/06/2022 6:48:33	00:00:10		
Closed	4966	2	channel_2		🖳 About VO	C-MDx Recorder					?	X	2022 6:22:14	13/06/2022 6:22:31	00:00:18		1
Closed	4965	1	channel_1										2022 6:22:14	13/06/2022 6:22:31	00:00:18		
							Maria Dantas										
					Voice	e C ollect	Recording v	er tor voice a worldwide	nd Data								
1				-									-			>	
Displaye	ed records: 15	i (1 - 15) / Filtered	: 15 / Total: 15		VC-MDx A	pplication Version 1	4.4.0.12										
					About: v11	ber: 83-DemoSvstem '	/DS ED137 20	220207 LEN	ovo								
					Constants	-)2015 2021//-:	C-II										
Start tim	e:		Calling No.:		Copyright (c) 2013-2021 Voice	Collect GmbH. /	All rights reser	vea.								
Stop time	e:		Called No.:		Visit http://w	www.voicecollect.de					🗸 OK						
Direction			Compressio	n:													
Record	D-		DSE-												())		2
Ticcorar										Vol	ume B	ack offs	et Duratio		Skip	DS	E
Short Co	mment		Save	Comment							• [10 🚞	(s) <u>60</u>	(s)	5 🗮 (s) 5	\Xi (s)
Reco	ording Change	Je	Record	ing Channels		-010-	Connected to 0 o	of 1 VOIP ser	ver(s)								
SHAC	tive Calls:0																
				L 2	3	4 5	6	7		8	9	10	11	12 1	3 1	4	^
				<i>—</i>	<u>*</u>	- 🏅 🏻 🚛	- <i>P</i> -			8				🚽 🕹 🚺	S 🖌 🖌	×	
IR Bu	iffer		Analog	Analog	Analog	Analog Analo	g Analog	Analog	An	alog	Analog	Analog) Analog	Analog Ana	alog Ana	alog	
I+ Fro	om: 13/06/2022	2 6:22:14	15	16	17	18 19	20	21	2	22	23	24	25	26 2	7 2	8	
+II To:	: 17/06/2023	2 2:00:22		1	122	1 🏫 🖉	<u>N</u>	1	1	7	1	12	1	1 1	P 1	3	
Deck	8		Analog	Analog	PCM	PCM PCM	PCM	PCM	P	СМ	PCM	PCM	PCM	PCM PC	M PO	CM	
⊘ NA	S: Ready, Use	ed 0%	29	30	31	32 33	34	35		36	37	28	39	40 4	1 4	2	
🥏 A: I	Ready, Used 8	%				- JZ - JJ										-2	
				PCM	PCM				ų	CM	PCM			4		TM	
Mess	sages		FCM	FCM	FCIM	PCM PCM	FCM	FCM	P	CM	I CIM	PCM	FCM	FCM PU	am PC	2141	¥
™Ner ▲ Free	w messages:) pings: 0)			.)		Advanced	channel info	rmation					
, - L I			4	Start All		stop All	Configurat	ion		Show all o	hannels						
										con all c							



3.3 Click SNMP service icon.

SRV3	- VC-MDx R	ecorder - IR Buffe	er Records - Super	1										- 0	I X
Lock V	iew <u>R</u> eco	ords <u>S</u> ettings	Service H	<u>l</u> elp											
	13	<u> (</u>		10	0 10	SNMP	?						3:4	[]:H	7
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca Marl	ked Direction	Start Time	Stop Time	Duration	Disc Lab	
Closed	4981	5	Analog				No		No		17/06/2022 3:04:04	17/06/2022 3:05:55	00:01:51		
Closed	4980	3	Analog				No		No		17/06/2022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Closed	4979	3	Analog				No		No		17/06/2022 2:28:30	17/06/2022 2:28:46	00:00:16	Sector Sectors	
Closed	4978	1	Analog				No		Yes		17/06/2022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
Closed	4977	3	channel_3				No		No		17/06/2022 1:57:19	17/06/2022 2:00:22	00:03:02		A mar
Closed	4976	1	channel_1				No		Yes		17/06/2022 1:54:44	17/06/2022 1:55:11	00:00:27		54
Closed	4975	1	channel_1				No		Yes		17/06/2022 1:53:22	17/06/2022 1:54:18	00:00:56		
Closed	4974	2	channel_2				No		Yes		16/06/2022 6:32:13	16/06/2022 6:32:29	00:00:16		A
Closed	4973	1	channel_1				No		Yes		16/06/2022 6:28:58	16/06/2022 6:29:53	00:00:55		10-10-
Closed	4972	1	channel_1				No		Yes		16/06/2022 6:01:40	16/06/2022 6:02:06	00:00:26		
Closed	4971	2	channel_2				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed	4970	1	channel_1				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed	4964	2	channel 2				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed	4963	1	channel 1				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed	4969	2	channel 2			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4968	1	channel 1			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4967	5	channel 5				No		No		13/06/2022 6:48:23	13/06/2022 6:48:33	00.00.10		NAME OF A
Closed	4966	2	channel 2				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00.00.18		-
Closed	4965	1	channel 1				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00.00.18		
Circled a	1000		Gildring_1								TO DO LOLL DILL. IT	100 000 2022 0.22.01	00.00.10		AND IL
															10- V
<														>	
D'	1	(1 10) / []]	10 /T + 1 10												
Displayed	Trecolds. 1:	r(1 - 13) / Finiered.	. 197 TOLAI. 19					_							
										Loop					
Start time			Calling No.:										-		8
Stop time			Called No.:												
Direction:			Compressio	n:											
Record	÷		DSE-							A A			· · · · ·	1)2	
110001010										Volume E	lack offset Duratio		Skip	DSI	
Short Cor	mment:		Save	Comment							10 🚍 (s) 60 🗆	(s) Flexi	5	s) 5	
									7		Provide Name				
Reco	rding Channe	de .	Record	ing Channels		-00-	Connected to 0	of 1 VOIP ser	ver(s)						
(in Acti	ve Calls: 0														
one muu	ve cons. e			2	3	4 5	6	7	8	9	10 11	12 13	1 1	4	<u>^</u>
				1	×	S 🔎		×	5			S (1	2 /	2	
IR But	ffer		Analog	Analog	Analog A	nalog Analo	og Analog	Analog	Analog	Analog	Analog Analog	Analog Anal	.og Ana	alog	
It From	m: 13/06/2023	6.22.14	15	16	17	18 19	20	21	22	23	24 25	26 27	1 1	8	
+II To:	17/06/2023	2 3:05:55	1	1			1	2	-	-		A		-	
					L L			DCM.		DCM.			. 4		
Decks			Analog	Analog	1.014	PCIV	FCM	FUM	FUM	FCM	I CIM PCM	rum PU	m PL	2141	
O NAS	5: Ready, Use	ed 0%	29	30	31	32 33	34	35	36	37	38 39	40 41	4	12	
-AL	Jecteu		J 🎦		12 1				1	122			2 🖸		
Mess	ages		PCM	PCM	PCM	PCM PCN	PCM	PCM	PCM	PCM	PCM PCM	PCM PC	M PC	CM	~
12 New	messages:	D													
/ Erro	ors: 0, A-War	nings: 0	Ec.	Start All	Stor	All)	Configurat	ion	Adva	inced channel info	ormation				
-)	0.01				Show	v all channels					

3.4 A window of SNMP Settings displayed then click Save.

🔐 SRV3 -	VC-MDx R	ecorder - IR Buffe	er Records - Super											- 0	×
<u>L</u> ock <u>V</u> ie	ew <u>R</u> ec	ords <u>S</u> ettings	<u>S</u> ervice <u>H</u>	<u>l</u> elp											
	13	sta 🔊	"	o) 10) 📷 (L 😹 🕜							2:5	4: {	3
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca Marked	Direction Start T	ìme	Stop Time	Duration	Disc Lab	
Closed	4980	3	Analog				No		No	17/06	/2022 2:29:13	17/06/2022 2:29:33	00.00.20	NAS 202	
Closed	4979	3	Analog				No		No	17/06	/2022 2:28:30	17/06/2022 2:28:46	00:00:16		
Closed	4978	1	Analog	Chill 4D Carting						~	122 2.23.21	17/06/2022 2:24:18	00:00:57	NAS 202	
Closed	4977	3	channel 3	SiviviP Settings						^	022 1:57:19	17/06/2022 2:00:22	00:03:02		
Closed	4976	1	channel 1								022 1:54:44	17/06/2022 1:55:11	00:00:27		-
Closed	4975	1	channel 1		Local Addre	ess: 10.10.10.12		•	Port: 161		022 1:53:22	17/06/2022 1:54:18	00:00:56		
Closed	4974	2	channel 2			,		_			022 6:32:13	16/06/2022 6:32:29	00:00:16		
Closed	4973	1	channel 1	Accept	ed community	names					022 6:28:58	16/06/2022 6:29:53	00:00:55		A 1000
Closed	4972	1	channel 1	Commu	unity		Rights				022 6:01:40	16/06/2022 6:02:06	00:00:26		
Closed	4971	2	channel 2	public			ReadOr	ıly			022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed	4970	1	channel 1								022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed	4964	2	channel 2								022 6:16:52	14/06/2022 6:16:59	00:00:07		100
Closed	4963	1	channel 1								122 6:16:52	14/06/2022 6:16:59	00.00.02		
Closed	4969	2	channel 2	SNMPv3 Au	thoritative Engi	ne					022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4968	1	channel 1	ID 41 25 2	5 69 43				ID is displa	yed as a hex string	122 6:50:45	13/06/2022 6:51:18	00.00.33		
	4967	5	channel 5						("xx-xxxx	-xx")	122 6:48:23	13/06/2022 6:48:33	00.00.10		`
Closed	4966	2	channel 2	Boots 2	Start Ti	me 16/06/2022 7:17:5	5				122 6:22:14	13/06/2022 6:22:31	00.00.18		1. In the second
Closed	4965	1	channel 1								122 6:22:14	13/06/2022 6:22:31	00.00.18		
Las Closed	4303		chamila_1	Users Table							0.22.14	13/00/2022 0.22.31	00.00.10		
				Name		Authentication Passy	vord Prot	ocol P	rivacy Password	Protocol					
				agentVoice	CollectAuth	auth	Sha			None					
<				agentVoice	CollectPriv	auth	Sha	рі	riv	TripleDes				>	
D: 1 1		1 10 / E'll	10/7 . 1 10	agentVoice	Collect		Non	e		None	-				
Displayed	records: I	s (1 - 18) / Filtered	: 187 10[a]: 18												ļ
Start time:			Calling No.:												
Stontime			Called No :												
Stop time.			Cullea No												
Direction:			Compression	י <u>ר</u>									- (1 (1	
Record ID:			DSE:	E			=				Duratia		Skin	ns	-
Short Com	ment			I VoiceCol	lect only suppo	rts SNMPv3	I Allo	ws engine I	D change			Flexi	экір		
Shortcom			ta Save								(3) 60		5 🗮 (s) 5	💼 (s)
r				Managers (for traps sendir	1g)									
Record	ding Chann	ale	Recordi												
(# Activ	ve Calle:0														
our root v	e cuito. e		1								11	12 13	1	4	^
									Sav	e Cancel	<u>×</u>	- J 🖉	r /	2	
IR Buff	fer		Analog				_				Analog	Analog Anal	og Ana	alog	
II+ From	n: 13/06/202	2 6:22:14	15	16	17	18 19	20	21	22	23 24	25	26 27	2	8	
+II To:	17/06/202	2 2:29:33	- I I 🔊	7	1999	ren 🖉	<u>)</u>	7	1	1 1	1	1 11	•	-	
Dealer			Analog	Analog	PCM	PCM PCM	PCM	PCM	PCM	PCM PCM	PCM	PCM PCI		M	
Decks	Dendu II-	-1.0%	Analog	Analog	04	- CM	I CIM	I CM	100	PCM PCM	1 CIVI	FCI FCI	- FV		
⊘ A: Re	eady, Used	5%	29	30	31	32 33	34	35	36	3/ 38	39	40 41	4	2	
					1 4		- 12	L			L		, L	1	
Messa	ges		PCM	PCM	PCM	PCM PCM	PCM	PCM	PCM	PCM PCM	PCM	PCM PCI	4 PC	-M	¥
New	messages:	0							Advance	d channel information					
/*Error	rs: 0, /\$+Wa	nings: 0	- ita	Start All	a Sto	p All	Configura	ation		a chamiler mornation					
									Show all	cnannels					

VoiceCollect

SNMP V2

SRV3 - VC-MDx	Recorder - IR Buff	fer Records - Supe	r												- 0	×
ock <u>V</u> iew <u>R</u> e	cords <u>S</u> etting	s <u>S</u> ervice <u>I</u>	<u>H</u> elp													
📑 🕉			' 🖒 I 🧐		् 👬 🤅										ide	
Status Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca.	Marked	Direction	Start Tim	1e	Stop Time	Duration	Disc Lab	
Closed 4980	3	Analog				No			No		17/06/2	022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Closed 4979	3	Analog				No			No		17/06/2	022 2:28:30	17/06/2022 2:28:46	00:00:16		
Closed 4978	1	Analog	SNMP Setting								×	022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
Closed 4977	3	channel_3										022 1:57:19	17/06/2022 2:00:22	00:03:02		
Closed 4976	1	channel_1						r				022 1:54:44	17/06/2022 1:55:11	00:00:27		
Closed 4975	1	channel_1		Local Add	ress: 10.10.10.12		–	Port:	161			022 1:53:22	17/06/2022 1:54:18	00:00:56		
Closed 4974	2	channel_2	Access	ad communit	(Damar							022 6:32:13	16/06/2022 6:32:29	00:00:16		
Closed 4973	1	channel_1	Accept	ed community	riames							022 6:28:58	16/06/2022 6:29:53	00:00:55		
Closed 4972	1	channel_1	Comm	unity		Rights						022 6:01:40	16/06/2022 6:02:06	00:00:26		1 T
Closed 4971	2	channel 2	public			ReadOnt	у					022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed 4970	1	channel 1										022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed 4964	2	channel 2										022 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed 4963	1	channel 1										022 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed 4969	2	channel 2	SNMPv3 Au	thoritative En	gine							122 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed 4968	1	channel 1	ID 41 25 2	5 69 43					D is displaye	d as a hex str	ring	122 6:50:45	13/06/2022 6:51:18	00.00.33		100
Closed 4967	5	channel 5							"xx-xxxx-xx	(")	-	122 6:48:23	13/06/2022 6:48:33	00.00.33		
Closed 4967	2	channel_2	Boots 2	Start T	Time 16/06/2022 7:17	:55						122 6:22:14	12/06/2022 0.40.33	00.00.10		in more than
Closed 4366	2	channel_2										022 0.22.14	13/06/2022 6:22:31	00.00.10		
Closed 4965	1	channel_1	Users Table									JZZ 6:22:14	13/06/2022 6:22:31	00:00:18		
			Name		Authentication Pas	sword Proto	col Pr	rivacy Pa	assword	Protocol	1					
			agentVoice	CollectAuth	auth	Sha				None						<u> </u>
c			agentVoice	CollectPriv	auth	Sha	pr	riv		TripleDe	s				>	
)isplayed records;	18 (1 - 18) / Filtere	d: 18 / Total: 18	agentVoice	Collect		None				None						
		_										_				
Start time:		Calling No.:														
Stop time:		Called No.:										_				
)irection:		Compressio	n												1 (13	_
Record ID:		DSE:													DOF	
			VoiceCol	lect only supp	orts SNMPv3	Allov	/s engine l	D chang	je –			Durato	Elexi	SKIP	DSE	
Short Comment:		Save	C									(s) <u>60</u> =	(s)	5 🚞 (s) 5	🚍 (s)
			Managers (for traps send	ing)											
Recording Chan	nels	Record	lür		Add											
Active Calls: 0		1	-) al ata							11	10 10		4	
					Jelete					_	-	1			4	<u>^</u>
<u> </u>		🖾		F	Properties				Save	Can	ICEI		a 🚛	T /		
IR Buffer		Analog					_	_	-	_		Analog	Analog Anal	og Ana	log	
II+ From: 13/06/20	22 6:22:14	15	16	17	18 19	20	21		22	23	24	25	26 27	2	8	
+II To: 17/06/20	22 2:29:33	N 1	7	1	1 2	N 10	7		1	1	1	1		•	-	
Daaka		Applos	Analog	PCM	PCM PCM	PCM	PCM		PCM	PCM	PCM	PCM	PCM PC	M PC	M	
CONTRACTOR INCOMENT		Allalog	Analog	- Cm	CM PCM	I CIM	I CIVI		1.011	1.011	7 Cm	100	FCM FC	- FC		
A: Ready, User	sed 0%	29	30	31	32 33	34	35		36	37	38	39	40 41	4	2	
- A. Heady, Osec			L	L 🔤		L	L		L 🔤	L 🔤	1	12	L 🔤 L	T []	-	
Messages		PCM	PCM	PCM	PCM PCM	РСМ	PCM		PCM	PCM	РСМ	PCM	PCM PC	M PC	.M	×
New messages Errors: 0, AND	: 0 arnings: 0		s Start All	-	top All	♦ Configurat	ion)	F	Advanced of	channel inform	mation					
						Connigurat		Г	Show all ch	nannels						

3.5 Right click on column Managers (for traps sending) and select Add.

SNMP V2

3.6 Window Remote Entity Configuration.

SRV3	3 - VC-MDx R	ecorder - IR Buff	er Records - Super												- 🗆	\times
Lock)	<u>V</u> iew <u>R</u> ec	ords <u>S</u> ettings	<u>S</u> ervice <u>H</u>	elp												
	7 🔗	sta 🔊	"	è 19) 🔟 🤇	२ 😹 🌘	2							2:5	8: {	3
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca Marke	ed Direction	Start Tim	ne	Stop Time	Duration	Disc Lab	
Closed	4980	3	Analog				No		No		17/06/2	022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Losed 2	4979	3	Analog				No		No		17/06/2	022 2:28:30	17/06/2022 2:28:46	00:00:16		
Closed	4978	1	Analog	SNMP Setting	s						\times	022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
Closed 2	4977	3	channel_3	-								022 1:57:19	17/06/2022 2:00:22	00:03:02		
Closed	49/6	1	channel_1			10 10 10 13			Port 161			022 1:54:44	1//06/2022 1:55:11	00:00:27		
Classed	49/5	2	channel_1		LUCAI AUU	1655. [10.10.10.12						022 1:03:22	17/06/2022 1:94:18	00.00.10		
Closed	4374	2	channel_2	Accep	ted community	/ names						022 0.32.13	16/06/2022 6:32:23	00:00:16		
Closed	4972	1	channel 1	Comm	unity		Rights					022 6:01:40	16/06/2022 6:23:33	00:00:35		
A Closed	4971	2	channel 2	public			ReadOnly	/				022 10:10:39	14/06/2022 10:11:00) 00:00:20		
Closed	4970	1	channel 1									022 10:10:39	14/06/2022 10:11:0	00:00:21		
Closed	4964	2	channel 2									022 6:16:52	14/06/2022 6:16:59	00:00:07		1
Closed	4963	1	channel_1	Remo	te Entity Conf	iguration				×		022 6:16:52	14/06/2022 6:16:59	00:00:07		
/ Closed	4969	2	channel_2	SIN								022 6:50:45	13/06/2022 6:51:18	00:00:33		1
Closed 😰	4968	1	channel_1	ID	Address		Bort 46	20 Ver	tion: G d	C 2 C 2	ing	022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4967	5	channel_5	Boo	Autress		Fon Inc	VGI.	siun. se y	203		022 6:48:23	13/06/2022 6:48:33	00:00:10		
Closed	4966	2	channel_2		Community:	public						022 6:22:14	13/06/2022 6:22:31	00:00:18		
Closed .	4965	1	channel_1	Use Us	er Authentica	tion and Privacy (v	3) ———					022 6:22:14	13/06/2022 6:22:31	00:00:18		
				Na			Ĩ									seen fi
				Nd and	Name											
<				age Aur	th Password			Aut		lone -	s	-			>	
Distant		D (1 10) / Elbarra	10/T-L 10	age		 			///010000/ [//			-				
Displaye	arecolus. I	s (1 - 16) / Fillered	. 107 TOLAI. 10	Pr	iv Password			Pn	v Protocol	lone 🔻						
				NC	DTE: SHA and	I TripleDes are con	noliant with FIP	S-140 stand	ards							
Start tim	e:		Calling No.:													
Stop time	e:		Called No.:						OK	Cancel						
Direction			Compression												1 (5	
Record I	D:		DSE:	_											DOL	-
Short Co	mmont			VoiceCo	llect only supp	orts SNMPv3	Allow	s engine ID (change			Uuratio	Flexi	экір	USE	=
SHOLCO			Ca Save									(8) 60		5 🗮 🤇	s) 5	🛨 (s)
ī				Managers ((for traps send	ing)]
Reco	ording Chann	els	Recordi													
Sta Act	tive Calls: 0												10 1			
										_	1	1	12 T	3	.4 🔊	<u> </u>
									S	ave Ca	incel	L .A.	્રે 🕌	i 🖉	~	
IR Bu	uffer		Analog								-	Analog	Analog Ana	log Ana	alog	
III Fro	om: 13/06/202	2 6:22:14	15	16	17	18 19	20	21	22	23	24	25	26 2	7 2	.8	
		2 2.20.00	- I I 🥭	4	L==		<u></u>	4	L	L==			u 🔤 🛛 🖓	🛋 L	<u> </u>	
Deck	s		Analog	Analog	PCM	PCM PCM	PCM	PCM	PCM	PCM	PCM	PCM	PCM PC	;M PO	CM	
2 NA	S: Ready, Us Roody, Used	ed 0%	29	30	31	32 33	34	35	36	37	38	39	40 4	.1 4	12	
	neady, Osed	J70		L 🔤				La c	L 🔤	L 🚘			L 🖾 L	2° L		
Mess	sages		PCM	PCM	PCM	PCM PCM	PCM	PCM	PCM	PCM	PCM	PCM	PCM PC	JM PO	CM	~
t⊠Ne	w messages:	0							CZ Adver	ond observal infe	rmation					
/•Err	ors: 0, />Wa	mings: 0	144	Start All	@S	op All	🤌 Configurati	on	Auvan	-U sharanta	aniauon					
									Snow	an channels						
Recc StarAct IR Bu IF Frc II To Deck © NA © A: I Mess SuNe Frr	Iffer If	2 6:22:14 2 2:29:33 ed 0% 5% 0 nnings: 0	Analog 15 Analog 29 PCM	16 Analog 30 PCM Start All	17 PCM 31 PCM	18 19 PCM PCM 22 33 PCM PCM PCM PCM	20 PCM 34 PCM	21 PCM 35 PCM	22 PCM PCM PCM Advan Show	23 PCM 37 PCM ced channel info	24 PCM 38 PCM armation	11 Analog 25 PCM 39 PCM	12 1 Analog An 26 2 PCM P 40 4 PCM P	3 1 Pilog Ana 7 2 DM PC 1 4 DM PC	4 Palog 28 CM 12 CM	~

3.7 Insert IP Address of PC receiver to receive SNMP traps and tick Version 2 then OK.

nub	nmunity lic		Rights ReadOnly		
pub			Readonly		
Rer	note Entity Co	nfiguration		1	×
	Address	10.10.10.61	Port 162	Version: C 1 🕫	2 C 3
	Community:	public			-
[[]	Jser Authentic	ation and Privacy (v	3)		
	Name				
4	Auth Password			Auth Protocol Non	e 👻
	Priv Password	1		Priv Protocol Non	e 🔻
9	NOTE: SHA ar	nd TripleDes are con	npliant with FIPS-14	, 0 standards.	
				OK	Cancel
oice	Collect only sup	ports SNMPv3	Allows eng	gine ID change	



SRV3	- VC-MDx	Recorder - IR Buffe	er Records - Super												- 🗆	×
Lock V	/iew <u>R</u> e	cords <u>S</u> ettings	<u>S</u> ervice <u>H</u>	elp												
	7 3	1	"	è 10) 🚺 C	K 😹 🤅								2:5	3:51	┫
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protect	ed Calleo	N Ca Mar	ked Direc	tion Start Ti	ime	Stop Time	Duration	Disc Lab	
Closed	4980	3	Analog				No		No		17/06/	2022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Closed	4979	3	Analog				No		No		17/06/	2022 2:28:30	17/06/2022 2:28:46	00:00:16		
Closed	4978	1	Analog	SNMP Setting							×	022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
X Closed	4977	3	channel_3	-								022 1:57:19	17/06/2022 2:00:22	00:03:02		
Closed	4976	1	channel_1					-	Port 161			022 1:54:44	17/06/2022 1:55:11	00:00:27		
Closed	49/5	1	channel_1		Local Addre	ss. [10.10.10.12						122 1:53:22	1//06/2022 1:54:18	00:00:56		
Closed	49/4	2	channel_2	Accept	ed community i	names						022 6:32:13	16/06/2022 6:32:29	00.00.55		
Closed	4373	1	channel_1	Comm	unity		Right	3				022 6:20:00	16/06/2022 6:23:33	00:00:35		
Closed	4972	2	channel_1	public			Read	Only				122 0.01.40	14/06/2022 0.02.00	00.00.20		
Closed	4970	1	channel 1									122 10:10:33	14/06/2022 10:11:00	00.00.21		
Closed	4964	2	channel 2									122 6:16:52	14/06/2022 6:16:59	00:00:21		200
Closed	4963	1	channel 1									122 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed	4969	2	channel 2	SNMPv3 Au	thoritative Engi	ne						022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4968	1	channel_1	ID 41 25 2	5 69 43				ID is dis	played as a l	hex string	022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4967	5	channel_5			46/06/2022 7:4	7.66		("xx-xx.	.xx-xx")		022 6:48:23	13/06/2022 6:48:33	00:00:10		
Closed	4966	2	channel_2	Boots 2	Start Fir	ne 10/00/2022 /.1	.55					022 6:22:14	13/06/2022 6:22:31	00:00:18		
Closed 2	4965	1	channel_1	Licere Table								022 6:22:14	13/06/2022 6:22:31	00:00:18		<u>Ta-</u>
				Name		Authentication Pas	sword Pi	otocol	Privacy Passwor	d P	rotocol					
				agentVoice	CollectAuth	auth	S	na		N	one					10° V
<				agentVoice	CollectPriv	auth	S	na	priv	T	ripleDes				>	
Displaye	d records: i	18 (1 - 18) / Filtered	: 18 / Total: 18	agentvoice	Jollect		N	one		N	one					
Start time			Calling No.:													
Stop time			Called No.:												_	
Direction			Compromion													
Descal			Der)	I 🖉 🕨 🖉 🖉 🖌 🗙	▼∫Þ∫	1/2	2
Record II			DSE:	VoiceCol	lect only suppo	rts SNMPv3		lows engin	e ID change			Duratio		Skip	DSI	
Short Co	mment		Save (iooroniy soppo				o ib chango			(s) 60	(s) Flexi	5 - (a) 5	- (s)
			-	Managers (for trans sendin	a)								3 1 1	, <mark>, ,</mark>	<u> </u>
				10 10 10 6	1:162											
Reco	rding Chan	nels	Recordi													
Sta Act	ive Calls: 0		- 1	1								11	12 13	1	4	^
										Cours.	Canaal	N 10	r 📧	P	>	
	"		Analog							save _	Calicer	Analog	Analon Anal	og Ana	loa	
IR BU	mer 	00 6:00:14	15	16	17	10 10	20		1 22	22	24	25	26 27		0	
+II To:	m: 13/06/20 17/06/20	22 0:22:14		-			20	h í		23	24	25	20 21		•	
				. 4						- 1			- Les Les	Г Ц		
Deck	s o o o o o	1.000	Analog	Analog	РСМ	PCM PCM	PCN			PCM	PCM	PCM	PCM PC	M PC	.171	
🥹 ΝΑ 😔 Δ · Ε	S: Ready, Us Ready, Used	sed 0% 5%	29	30	31	32 33	34		5 36	37	38	39	40 41	4	2	
			\prec \square	1	12		L			12		12		5 L		
Mess	ages		PCM	PCM	PCM	PCM PCM	PCM	I P	CM PCM	PCM	PCM	PCM	PCM PC	M PC	:M	~
12 Nev	w messages	.0							Adva	nced charge	Linformation					
/►Em	ors: 0, /&Wa	irnings: 0	144	Start All	a Sto	o All	🤌 Configu	iration	Auva	all shows t	mornation					
									Show	all channels						

3.8 IP Address of PC receiver to receive SNMP traps has been Add then Save.

SNMP V2

4 Operating of SNMP MIB

4.1 Open "ManageEngine MibBrowser" application.

ManageEngine MibBro	owser Free Tool	- ¤ ×
è 🛃 🖬 🚳 🕫	a Ta 🗐 🜮 🔨 🗠 💷 👹 🗶 🚭 🧠 🔳 🖬 🗇 🌒 🚺 🖉 🖉	
Coaded NibModules	Host 10.10.10.12 · Port 161	~
	Community •••••• Write Community	
	Device Type	
	Device Type Identified Not Available C Reload	
	Suggested OIDs None v	
	Object ID	
		^
		×
	Description Multivar	
	Syntax Status Reference	
	Index	
<	> Objed ID	
	Description	
Global View		

4.2 Select Edit and choose Settings. Choose SNMP Version tick v2c then OK.

ile Edit View Operations He	MibBrowser Settings ×	
è 🍰 🗈 🕺 🖻	General Mib Settings Template Settings	Download More Free Tools
Loaded MibModules	SNMP Version Ov1 0 v2 Ov3	~
	General Options Get Bulk Options Time Out 5 Retries 0 Encoding ISO8859_1	C Reload
	V3 Options V3 Options Context Name Context ID Context ID	
1	V3 Settings Save V3 Settings to File Save V3 Settings to Database Database Settings	
	User Secu Auth Priv Auth Priv Targ Targ Engi Entity	
<	Add Modify Delete	
	Restore Defaults OK Cancel	

4.3 From menu bar "File" select "Load MIB", then select a MIB file.

ManageEngine Mibl	Browser F	ree Tool											-		×
e Edit View Operat	tions He	lp													
Load MIB	Ctrl+0	🔚 🧌 🔊	1	🖄 🖽	👋 💰	🌚 🤞	b 🔤 🛛	🖬 🎒 🍕	More	Free Tools					
UnLoad MIB	Delete									_		1			
Load All MIBs	Ctrl+A	Host	10.10.1	0.12						Port		161			
UnLoad All MIBs	Ctrl+U	Community	•••••							Write	Community				
Save Results As	Ctrl+S	Set Value								~					
Print Results	Ctrl+P	Device Type													
VC-MIB		Device Type Ider	ntified	Not Available							C F	Reload			
F-0		Suggested OIDs	s	None							\sim				
Exit		Object ID													
															_
	- IP	Description in the													
	- II.	Description MultiVa	ar												
		Syntax									Status		_	_	_
		Index		-							releience				_
	>	Object ID		-									_	_	_
1 N		o o jour io													_
abal View	_	Description													
obai view 🛄															

ManageEngine MibBrowser	er Free Tool - 🗆	×
File Edit View Operations H	Help	
📥 🎂 🖥 🐴 🏷	፝፟፟፟፟፟፟ ፟፟፟፟ ፟፟፟፟፝ ፟፟ ፟፟፟ ፟፝ ²	
Coaded MitModules	Image: Constraint of the set of the se	
	Recent Items Desktop Documents This PC	v
< >> Global View	Description Syntax Access Network File name: VoiceCollectRecorderv2.mb Open Cancel Status Reference Cancel	



4.4 The list of SNMP OID (Object ID) displayed.

ManageEngine MibBrowser Free Tool				-	×
🚵 🍰 🖻 🕺 🖺 🖻 🖀 🖓 🔊 🏹 🖉	i 🖿 👹 🛫	: 🚭 🧠 🔳 🖬 🖨 🧇 🚺	Download More Free Tools		
Coaded MikMobiles VoltB VoltB Content VoltB Content VoltB Content VoltB Vol	Host Community Set Value Device Type Device Type Ider Suggested OIDs Object ID Loading MIBs C:W Done.	10.10.10 12	Port Write Communit	161 C Rebad	
recorderUserLogoffSuccessful	Description Multiv	ar			
recorderKeepAlve vcRecorderConformance	Syntax Access Index		Status Reference		
Global View	Object ID Description				

4.5 Right click on a SNMP OID then select "GET" or "GETNEXT" to obtain the selected SNMP data(s) from VC-MDx Recorder.

ManageEngine MibBrowser Free Tool						-		×	
File Edit View Operations Help									
🚵 📥 🗄 🔁 🖻 🖀 🗊 🔨 🍏 🗉	🛅 🐞 🗹	. 🧐 🐵 🖪 🗟 🏈 🚺 Download More Free Tools							
Loaded MibModules	Host	10.10.10.12	~ Port	rt	161			~	
enterprises C	Community	•••••	Writ	ite Community					
B- 🔁 vcRecorder Se	Set Value		~	~					
ecorderTraps	Device Type								
recorderData	ne Ider	ntified Not Available			C. Reload				
- % recorderModel GE1	dolDa	None							
GEINEXI	id OID's	None		Ť					
recorderDeckNo View MIB Desc	cription .it	.iso.org.dod.hternet.private.enterprises.atis.vcRecorder.recorderData.recordererManufacturer.0							
- % recorderPresence Find Node								-	
recorderNetAdminCirem	outuring milds Cill	Users/vcuser/Documents/voiceCollectRecorderv2.mib							
recorderNetLCRClient	one.	10 10 10 10 12 : 161							
"% recorderNetCSTAClient	136121120	13614129133							
recorderS2maSyncCard re	ecordererManuf	nufacturer.0 VoiceCollect							
% recorderUP0SyncCard									
recorderRecordingStatus									
- % recorderChannelStatus									
- % recorderDbOperations									
- % recorderNetVDSServer									
- % recorderConnectedVDSServers									
- '% recorderMediaAlmostFull									
recorderButterAlmostFull									
······································									
👒 recorderUserLogonSuccessful								~	
recorderUserLogonFailed	escription MultiVa	x							
"% recorderEventDescription Sv	Syntax	DisplayString		Status ou	rrent				
recorderKeepAlive Ac	ccess	read-only		Reference				_	
with vorcecorderConformance	ndex								
01	bject ID	.1.3.6.1.4.1.29133.11.3.1							
		"Recorder manufacturer: VoiceCollect Gmb	8"						
Global View	rescription								

4.6 Right click on a SNMP OID folder then select "SNMPWALK" to obtain the all SNMP data(s) from VC-MDx Recorder.

Managerngine Mibbrowser Free Tool		-	a ×			
File Edit View Operations Help 🏊 🚣 🛐 🐴 🗞 🌇 🀜 ன 🗊 💅 🎋 🎼 🥅	🛎 🛫 🚭 💿 🗖 📮 🕾 🚱 🚺 🔐					
Loaded MibModules						
B-O VC-MIB Host	10.10.10.12	V Polt 161				
⊖ → atis Comn	munity •••••	Write Community				
🔄 🔄 vcRecorder Set Va	alue	v				
recorderTraps	ce Type					
GETNEXT Device	ee Tune Identified . Net Available	Cl Dalard				
recorder Churchark	je rype identilied i like Avalable	C Kedau				
- % recorde Sugg	jested OIDs None	✓				
- '% recorde View MIB Description Dhier	TID .iso.org.dod.internet.orivate.enterprises.atis.vcRecorder.recorderDr	ta				
Find Node						
- Sent G	SET request to 10.10.10.12 : 161					
- % recorderNetWstClient record	dererManufacturer.0	VoiceCollect				
- % recorderNetLCRClient record	derModel 0	VoiceCollect Recorder				
% recorderNetCSTAClient	derinCh 0	29				
recorderNetRC4000Client	derOutCh 0	2				
recorderUP0SyncCard record	derDacklie 0	1				
- % recorderRecordingStatus	derDeckno.0	l Deserved en esté at				
- % recorderRecordsInLastInterval	der Presence.0	Ne desirietetete economia d				
- '% recorderChannelStatus record	Jerwerkalminchent.u	No Administrator connected				
recorderDoOperations record	JerwetyvstChentu	No workstation connected				
recorderRegisteredVDSServers	JernetLCRChenLU	No LCR connected				
- % recorderConnectedVDSServers	JernetCSTAClient.0	No ARCP/CSTA connected				
% recorderMediaAlmostFull record	derNetRC4000Client.0	No RC4000 connected				
% recorderBufferAlmostFull record	derS2maSyncCard.0	No info available				
recorderRestarrArterPowerDown record	derUP0SyncCard.0	No info available				
record	derRecordingStatus.0	Recording started				
" recorderUserLogonFailed record	derRecordsInLastInterval.0	0 records in last interval				
- % recorderUserLogoffSuccessful record	derChannelStatus.0	28/10/2021 21:41:15 Total channels: 28, noop: 0, NoSync: 0, enabled: 28, active: 0				
record record record record	derDbOperations.0	0 database operations				
vcRecorderConformance record	derNetVDSServer.0	VDS Server 10.10.10.12 connected				
record	derRegisteredVDSServers.0	1				
record	derConnectedVDSServers.0	1				
record	derMediaAlmostFull.0	Media is 95% full				
record	derBufferAlmostFull.0	No info available				
record	derRestartAfterPowerDown.0	Recorder restarted after nower down				
record	derChannellnactivity 0	There was no activity on channel 8				
record	derUserLogon Successful.0	VC-MDx Recorder SRV3: User 'Super' unlocked the applicati				
	-	on.				
record	derUserLogonFailed.0	No info available				
record	derUserLogoffSuccessful.0	VC-MDX Recorder SRV3: User Super locked the application				
record	derEventDescription.0	No info available				
record	derKeepAlive.0	2021-10-28,21:40:37.312				
Descrip	otion MultiVar					
0000		Olahua aureat				
Syntax	χ	Status current				
	-5	Reference				
Acces						
Acces Index						
Acces Index Object	tID .1.3.6.1.4.1.29133.11.3	Conception and the second seco				

5 Operating of SNMP TRAP

5.1 Open "ManageEngine MibBrowser" and click "View" on menu bar and select "Trap Viewer".



5.2 Insert IP address of VC-MDx Recorder machine on "TrapParser" then click Add and Start.

8 🗄 🗄		1 🗐 🔊 🍕	🖄 🛅 👋 🖉	2 🐵 🧠 🔚		Oownl Downl More Fre	load ee Tools
Loaded MiDModule	es 🌂 TrapViewe	er			- C	ı ×	~
	Class	Туре	Source	Date	Message		
						_	
	Authentica	ate v1/v2c traps (Con	nmunity)	🗌 Enal	ble Logging Log	Format ~	
	Authentica	ate v1/v2c traps (Con ate v3 Trap	nmunity)	🗌 Enal	ble Logging Log ble Mail Config	Format ~ gure Mail	,
	Authentica	ate v1/v2c traps (Con ate v3 Trap 162	nmunity) TrapList	☐ Enal ☐ Ena 162:public →	ble Logging Log ble Mail Config Add	Format ~ gure Mail Del	
	Authentica Authentica Authentica Port Community	ate v1/v2c traps (Con ate v3 Trap 162 public	TrapList TrapParser	Enal	ble Logging Log ble Mail Config / Add	Format ~ jure Mail Del Load	
	Authentica Authentica Authentica Port Community Start	ate v1A2c traps (Con ate v3 Trap 162 public Stop	TrapList TrapParser Show Det	Enal Enal Enal Enal Io2:public v 10.10.10.12 ails Delete E	ble Logging Log ble Mail Config Add	Format ~ gure Mail Del Load	
	Authentica Authentica Authentica Port Community Start Tr	ate v1/v2c traps (Con ate v3 Trap 162 public Stop aps : 0 Inform : 0	TrapList TrapParser Show Det	Enai	ble Logging Log ble Mail Config Add Intry Parse TrapList	Format V pure Mail Del Load erEditor	

5.3 The window "TrapViewer" is running.

ManageEngine Mib File Edit View Operat	Browser Free Too tions Help	1				_	×
🇞 🛃 🛃	•	🗊 🔊 🔨 🖄	🛅 🐞 🛫 🔤	00 🔤 日	3 🔷 🚺	Download More Free Tools	
ቆ Loaded MibModules	🔨 TrapViewer	172 [>	<	~
	Class	Туре	Source	Date	Message	-	
	an The						^
	Authenticat	e v1/v2c traps (Commu	nity)	Enable Lo	gging Log Format		
	Authenticat	e v3 Trap		Enable Ma	ail Configure Mai	Mail	
	Port	162	TrapList 16	2:public 🗸	Add Del		
	Community	public	TrapParser 10.	10.10.12	Load		*
	Start	Stop	Show Details	Delete Entry	ParserEditor		
	Tra	aps : 0 Inform : 0	Statu	is : Listening for Trap	DS		
<	> Object	ID					
Global View 🗌	Descrit	otion					

5.4 The "TrapViewer" is getting a Trap data from VC-MDx Recorder.

💐 Traj	Viewer			– 🗆 X							
Class	Туре	Source	Date	Message							
Clear	v2c Trap	10.10.10.12	Mon Jun 20 02:34:43	ET 2022.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 3							
Clear	v2c Trap	10.10.10.12	Mon 1								
Clear	v2c Trap	10.10.10.12	Mon 1 map Deta								
Clear	v2c Trap	10.10.10.12	Mon 1								
Clear	v2c Trap	10.10.10.12	Mon	0 hours, 39 minutes, 7 seconds.							
Autr Autr Autr Port Commu	ienticate v1 ienticate v3	//2c traps (Comm Trap !	Enterprise Generic Type Specific Type Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 39 minutes, 7 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.22: .1.3.6.1.4.1.29133.11.3.16.0: 20/06/2022 7: 04: 43 Total channels: 66, noop: 8, NoSync: 40, enabled: 16, active: 0:							
Comme	Start	Stop	Severity	Clear							
EXT	Trope	E Inform : 0	Entity	10.10.12							
	Inaps .		RemotePort	161							
			LocalPort	162							
			Community	public							
			Node	10.10.12							
			Source	10.10.12							
			TimeReceive	Mon Jun 20 02:34:45 VET 2022							
			HelpURL	0-0.html							

5.5 Double click that Trap data then a window "Trap Details" displayed for the message.

🍕 Traj	oViewer			
Class	Type	Source	Date	Message
Clear	v2c Trap	10.10.10.12	Mon 1	1 2222 1.5.0.12.1.1.5.0. Hitelicks of load \$7.5.0.
Clear	v2c Trap	10.10.10.12	Mon 1 A Trap Details	X
Clear	v2c Trap	10.10.10.12	Mon 3	
Clear	v2c Trap	10.10.10.12	Mon 1 TimeStamp	0 hours, 39 minutes, 7 seconds,
Clear	v2c Trap	10.10.10.12	Mon 1 Enterprise	
			Generic Type	
Auth	nenticate v1. nenticate v3	V2c traps (Comn Trap	nunity) Message	
Port	162			40, enabled: 16, active: 0:
Commu	inity pub	ic	1 Sauaritu	Norsky and Market and M
	Start	Stop	Severity	Clear
	Traps	6 Inform · 0	Entity	10.10.12
			RemotePort	161
			LocalPort	162
			Community	public
			Node	10.10.12
			Source	10.10.12
			TimeReceived	Mon Jun 20 02:34:45 VET 2022
			HelpURL	0-0.html

6 SNMP TRAP Samples

Below is the sample images correlation between message on VC-MDx Recorder and SNMP Trap

6.1 VC-MDx Workstation: Connected

{.1.3.6.1.4.1. 29133.11.3.8.0} - VC-MDx Workstation :Connected

🍕 Trap	Viewer				×
Class	Туре	Source	Date	Me	ssage
Clear Clear	v2c Trap	10.10.10.12	Mon Jun 20 02:1	🎒 Trap Details	- O X
Clear	v2c Trap	10.10.10.12	Mon Jun 20 02: 1	TimeStamp Enterprise Generic Type Specific Type	0 hours, 22 minutes, 14 seconds.
Authenticate v1/v2c traps (Community) Authenticate v3 Trap			nunity)	Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 22 minutes, 14 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.18: .1.3.6.1.4.1.29133.11.3.8.0: Workstation SRV3 connected:
Port	162		TrapList	Severity	Clear
Commu	nity public		TrapParse	Entity	10 10 10 12
S	Start	Stop	Show D	RemotePort	161
000	Traps :	3 Inform : 0		LocalPort	162
				Community	public
				Node	10.10.12
				Source	10.10.12
				TimeReceived	Mon Jun 20 02:17:52 VET 2022
				HelpURL	0-0.html

6.2 VC-MDx Workstation : disconnected

{.1.3.6.1.4.1. 29133.11.3.8.0} - VC-MDx Workstation : disconnected

🔨 Trap	Viewer				- 🗆 X		
Class	Туре	Source	Date	Me	ssage		
Clear Clear	v2c Trap v2c Trap	10.10.10.12	Mon Jun 20 02:1	🍰 Trap Details		1000	×
		1		TimeStamp Enterprise Generic Type Specific Type	0 hours, 22 minutes, 56 seconds.		
Authe	enticate v1A enticate v3 1	v2c traps (Comn Trap	nunity)	Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 22 minutes, 56 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.18: .1.3.6.1.4.1.29133.11.3.8.0: Workstation SRV3 disconnected:		
Port	162		TrapList	Severity	Clear		
Commun	nity publi	c	TrapParse	Entity	10.10.10.12		
S	tart	Stop	Show D	RemotePort	161		 -1
000	Traps :	2 Inform : 0		LocalPort	162		 -1
				Community	public		
				Node	10.10.12		
				Source	10.10.12		
				TimeReceived	Mon Jun 20 02:18:33 VET 2022		
				HelpURL	0-0.html		
						_	

6.3 VDS Connected

{.1.3.6.1.4.1. 29133.11.3.23.0} - VDS Connected

SRV3	- VC-MDx	Recorder -	IR Buffer Records - Su	per											×
Lock <u>V</u>	(iew <u>R</u> e	ecords §	<u>S</u> ettings <u>S</u> ervice	<u>H</u> elp											
	13		J 💻 🗊	li 🌼 1	1	९ 😹 🕜		_					3:2	5:8	$\{ < $
Status	Record ID	Channel	Num Channel Nam	e User ID	Case	Short Comment	Protected	Called N	Ca Mar	ked Direction	Start Time	Stop Time	Duration	Disc Lab	
Closed	4981	5	Analog				No		No		17/06/2022 3:04:04	17/06/2022 3:05:55	00:01:51		
Closed	4980	3	Analog				No		No		17/06/2022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Closed	4979	3	Analog				No		No		17/06/2022 2:28:30	17/06/2022 2:28:46	00:00:16		
Closed	4978	1	Analog				No		Yes		17/06/2022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
Closed	4977	3	channel 3				No		No		17/06/2022 1:57:19	17/06/2022 2:00:22	00:03:02		A REAL PROPERTY AND
Closed	4976	1	channel_1				No		Yes		17/06/2022 1:54:44	17/06/2022 1:55:11	00:00:27		
Closed	4975	1	channel_1				No		Yes		17/06/2022 1:53:22	17/06/2022 1:54:18	00:00:56		
Closed 🖗	4974	2	channel_2				No		Yes		16/06/2022 6:32:13	16/06/2022 6:32:29	00:00:16		A
Closed	4973	1	channel 1				No		Yes		16/06/2022 6:28:58	16/06/2022 6:29:53	00:00:55		
Closed	4972	1	channel 1				No		Yes		16/06/2022 6:01:40	16/06/2022 6:02:06	00:00:26		
Closed	4971	2	channel_2				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		
Closed	4970	1	channel_1				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		5-
Closed	4964	2	channel_2				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
Closed	4963	1	channel_1				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		-
Closed 🤌	4969	2	channel_2			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
Closed	4968	1	channel_1			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		- T
Closed	4967	5	channel 5				No		No		13/06/2022 6:48:23	13/06/2022 6:48:33	00:00:10		Here of the
Closed	4966	2	channel 2				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00:00:18		te V
Closed	4965	1	channel 1				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00:00:18		
-															pand L
															<u>Ta-</u>
<														>	
Displaye	d records:	19 (1 - 19) /	Filtered: 19 / Total: 19												
										Loop					
Start time			Calling N	o.:											
Stontime			Called N												0
D:															
Direction			Compres	SIGIL						14 44	b (II (b) (I	N (N.) (🕑 (X	• ()	1/5	N
Record II):		DSE:							Volume F	Back offert Duratio		Skin	DS	F
Short Co	mment		[] s	ve Comment						_		(s) Flexi		->	-
													5 🗔 (s) <u>5</u>	(S)
Reco	rding Char	inels	Messa	iges											
Si Acti	ive Calls: 0	1	Messa	ine								Ackno	wledged		
			(1)17	06/2022 3-28-14 10	10 10 12 VDS	connected						NO			
			(¥'''	00/2022 0.20.14 10	.10.10.12.400	Connected						NO			
IR Bu	ffer														
I+ Fro	m: 13/06/20	022 6:22:14													
• 10:	17/06/20	322 3:00:00													
Decks	5														
NAS	5: Ready, L	lsed 0%													
🧼 A: E	jected														
Maga															
Mess	ages		51		Acknow	dedae All	Delete) ×	Delete All						
/► Erro	ors: 0. AN	arnings: 0						<u> </u>)					

🐔 Trap	Viewer				— 🗆 X
Class	Туре	Source	Date		Message
Clear	v2c Trap	10, 10, 10, 12	Mon Jun 2	0 02:15:03 VET 20	22.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 1
Clear	v2c Trap	10, 10, 10, 12	Mon Jun 2	True Dataila	
Clear	v2c Trap	10.10.10.12	Mon Jun 2	irap Details	
	12.00			TimeStamp Enterprise Generic Type Specific Type	0 hours, 19 minutes, 34 seconds.
Auth	enticate v1A enticate v3 1	2c traps (Comm Trap	iunity)	Message	1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 19 minutes, 34 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.18: .1.3.6.1.4.1.29133.11.3.21.0: VDS Server 10.10.10.12 connected:
Port	162		Tra		.1.3.6.1.4.1.29133.11.3.23.0: INTEGER: 1:
Commu	nity public	:	Trap	Severity	
S	itart	Stop	S	e m	Clear
	Traps :	4 Inform : 0		RemotePort	10.10.10.12
				LocalPort	162
				Community	public
				Node	10.10.12
				Source	10.10.12
				TimeReceived	Mon Jun 20 02:15:12 VET 2022
				HelpURL	0-0.html

6.4 User logged off/locked successful from the recorder

{.1.3.6.1.4.1. 29133.11.3.30} – User logged off/locked successful from the recorder

•	SRV3 - VC-MDx Recorder - IR Buffer Records - Super	
	SVVJ- VL-HUU Hecode- IK Buffer Hecode - Suger	Vac name Passaced Four eyes passaced Remember are
		Change password V OK XCancel
	A ∨ F	Active channels: 0 of 28 /DS connected: 1 of 1 RAB connected: 0 of 0 Buffer: 1% filled
		Anim connected. No Aessages: 0 errors 1 warnings Active client connections: 2

🍕 Trap	Viewer				– 🗆 X
Class	Туре	Source	Date		Message
Clear	v2c Trap	10.10.10.12	Mon Jun	20 02:06:03 VET 20	22.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 1
Clear	v2c Trap	10.10.10.12	Mon Jun	Trap Details	
Clear	v2c Trap	10.10.10.12	Mon Jun	inap Details	A L -
Clear Auth	enticate v1	10.10.10.12	Mon Jun	TimeStamp Enterprise Generic Type Specific Type Message	0 hours, 10 minutes, 26 seconds.
Commu	nity out	lic			
Commu	They pub	Ctan	IIa	Severity	Clear
5		Stop		Entity	10.10.10.12
	Traps :	4 Inform : 0	_	RemotePort	161
				LocalPort	162
				Community	public
				Node	10.10.12
				Source	10.10.12
				TimeReceived	Mon Jun 20 02:06:03 VET 2022
				HelpURL	0-0.html

6.5 User logged on/unlocked failed on the recorder

{.1.3.6.1.4.1. 29133.11.3.29} - User logged on/unlocked failed on the recorder

🔛 SRV	/3 - VC-	-MDx Recorde	er - IR Buffei	Records - Supe	r										- 0	×
<u>L</u> ock	<u>V</u> iew	<u>R</u> ecords	<u>S</u> ettings	<u>S</u> ervice <u>I</u>	<u>H</u> elp											
	1	3 🐔		_	n 🔊 🖉		ኣ 😹 🕜]: {	7;21	
Status	Reco	ord ID Chan	nel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca Marked	Direction	Start Time	Stop Time	Duration	Disc Lab	
	d 4981	1 5		Analog				No		No		17/06/2022 3:04:04	17/06/2022 3:05:55	00:01:51		
Close	d 4980) 3		Analog				No		No		17/06/2022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Close	d 4979	9 3		Analog				No		No		17/06/2022 2:28:30	17/06/2022 2:28:46	00:00:16		
Close	d 4978	3 1		Analog				No		Yes		17/06/2022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
Close	d 4977	7 3		channel_3				No		No		17/06/2022 1:57:19	17/06/2022 2:00:22	00:03:02		International Action
Close	d 4976	6 1		channel_1				No		Yes		17/06/2022 1:54:44	17/06/2022 1:55:11	00:00:27		
Close	d 4975	5 1		channel_1				No		Yes		17/06/2022 1:53:22	17/06/2022 1:54:18	00:00:56		
P Close	d 4974	4 2		channel_2				No		Yes		16/06/2022 6:32:13	16/06/2022 6:32:29	00:00:16		
Close	d 4973	3 1		channel_1				No		Yes		16/06/2022 6:28:58	16/06/2022 6:29:53	00:00:55		
Close	d 4972	2 1		channel_1				No		Yes		16/06/2022 6:01:40	16/06/2022 6:02:06	00:00:26		
🎤 Close	d 4971	1 2		channel_2				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		-
😰 Close	d 4970) 1		channel_1				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		lla-
🔑 Close	d 4964	4 2		channel_2				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
Close	d 4963	3 1		channel_1				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		-
🎤 Close	d 4969	9 2		channel_2			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
😰 Close	d 4968	3 1		channel_1			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		-
😰 Close	d 4967	7 5		channel_5				No		No		13/06/2022 6:48:23	13/06/2022 6:48:33	00:00:10		
🔑 Close	d 4966	6 2		channel_2				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00:00:18		Ta-
Close 😰	d 4965	5 1		channel_1				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00:00:18		
																10- V
<															>	
Display	ed rec	ords: 19 (1 - 19	9) / Filtered:	19 / Total: 19												
	_					_		_	_		_]
											Loop					
C1				C-11: N						-						
	ne.															
Stop tir	ne:			Called No.:												
Directio	n :			Compressio	n:					_					1 (**	
Record	ID:			DSE:												2
		_			_					Vol	lume Ba	ack offset Duratio	Elevi	Skip	DS	E
Short C	ommen	nt		Save	Comment						i /	10 📩 (s) 🛛 60 🗄		5 🚞 (s) 5	🕂 (s)
	_	_	_			_		_	_					_		_
				Message												
Rec	ording	Channels			·											
A 🕮 A	ctive Ca	alls: O		Message									Ackno	wledged		
				17/06	/2022 3:15:57 Unlo	cking the applic	ation failed - bad usem	ame or passwo	rd(User ")				NO			
	uffor			17/06.	/2022 3:15:56 Unlo	cking the applic	ation failed - bad usem	ame or passwo	rd(User 'User)			NO			
	uner 10	0000000.000		17/06	/2022 3:07:46 Deck	A: No disk in u	init.						NO			
+1 T	n: 17	/06/2022 6:22:1	55													
Dec	ks															
2 N	AS: Rea	ady, Used 0%														
	Ejecter	u														
Mes	sages															
SIN	ew mes	sages: 3		√ Ack	nowledge	✓ Acknowled	lge All 🔰 🚿	Delete	X	Delete All						
Æ	rrors: 0,	/warnings:	1						<u> </u>							
-	_															

🐔 Trap	pViewer				– – ×
Class Clear	Type v2c Tra	Source ap 10.10.10.12	Date Mon Jun	20 02:09:24 VET 20	Message 22 1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 1
				🛃 Trap Details	X
				TimeStamp Enterprise	0 hours, 13 minutes, 46 seconds.
				Generic Type	
Auth	ienticate ienticate	v1/v2c traps (Com v3 Trap	munity)	– Specific Type Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 13 minutes, 46 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.28: .1.3.6.1.4.1.29133.11.3.29.0: VC-MDx Recorder SRV3: Unlocking the application failed - b
Port	1	162	Т		ad username or password(User 'Supers'):
Commu	inity 🛛	oublic	Tra	p Severity	
1	Start	Stop	5	Entity	
	Trap	s : 1 Inform : 0		RemotePort	161
				LocalPort	162
				Community	public
				Node	10.10.12
				Source	10.10.12
				TimeReceived	Mon Jun 20 02:09:24 VET 2022
				HelpURL	0-0.html

6.6 User logged on/unlocked successful on the recorder

{.1.3.6.1.4.1. 29133.11.3.28} - User logged on/unlocked successful on the recorder

				🎒 Trap Detail	s – 🗆 X
				TimeStamp	0 hours, 54 minutes, 45 seconds.
				Enterprise	
				Generic Type	
🍕 TrapView	er			Specific Type	
Class	Туре	Source	Date		
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	D: Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 54 minutes, 45 seconds.:
Clear	v2c Trap	10.10.10.12	2 Mon Jun 20 02:5	D:	.1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.27:
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	D:	.1.3.6.1.4.1.29133.11.3.28.0: VC-MDx Recorder SRV3: User 'Super' unlocke
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	D:	d the application .
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	D:	
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	1:	
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	1: Countity	Towns of the second sec
Clear	v2c Trap	10, 10, 10, 12	2 Mon Jun 20 02:5	1: Seventy	Clear
Authentica	ate v1/v2c traps (Commun	iity)	Enable	Entity	10.10.10.12
Authentica	ate v3 Trap		Enable	RemotePort	161
Port	162	TrapList	162:public v	LocalPort	162
Community	public	TrapParser	10.10.10.12		
Start	Stop	Show Detail	s Delete Ent	Community	public
	raps : 8 Inform : 0	S	itatus : Listening for T	ra Node	10.10.10.12
				Source	10.10.10.12
				TimeReceived	Mon Jun 20 02:50:23 VET 2022
				HelpURL	0-0.html

6.7 Recording Started.

{.1.3.6.1.4.1. 29133.11.3.14} - Recording Started.

🔨 Trap	Viewer				- 0 X		
Class	Туре	Source	Date		Message		
Clear	v2c Trap	10.10.10.12	Mon Jun 2	20 02:02:42 VET 20:	12.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 7		
Clear	v2c Trap	10.10.10.12	Mon Jun :	🖉 Tran Detaile			×
Clear	v2c Trap	10.10.10.12	Mon Jun :				^
	V2c Hap	10.10.10.12	, הסכ חסרין	TimeStamp Enterprise Generic Type	0 hours, 7 minutes, 5 seconds.	 	
Auth	enticate v1 enticate v3	N2c traps (Comn : Trap	nunity)	Specific Type	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 7 minutes, 5 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.20: .1.3.6.1.4.1.29133.11.3.14.0: Recording started:	 	
Port	163	2	Tra	ł			
Commu	nity pub	lic	Trap	Severity	Clear		
ŝ	Start	Stop	S	Entity	10.10.10.12		
000	Traps	4 Inform : 0		RemotePort	161		
				LocalPort	162		
				Community	public		
				Node	10.10.10.12		
				Source	10.10.10.12		
				TimeReceived	Mon Jun 20 02:02:42 VET 2022		
				HelpURL	0-0.html		

6.8 VC-MDx Administrator : Connected

{.1.3.6.1.4.1. 29133.11.3.28} - VC-MDx Administrator : Connected



🐔 Trap	Viewer											
Class	Туре	Source	Date		Message							
Clear	v2c Trap	10.10.10.12	Mon Ju	in 20 02:22:43 VE	T 2022 1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 2							
Clear	v2c Trap	10.10.10.12	Mon 1	Tran Details		-		×				
Clear	v2c Trap	10.10.10.12	Mon 1	indp b ccuits								
				TimeStamp Enterprise	0 hours, 27 minutes, 5 seconds.							
🗹 Auth	enticate v1	I/v2c traps (Comn	nunity)	Specific Type Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 27 minutes, 5 seconds.:							
Auth	enticate v3	3 Trap			.1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.18:							
Port	16	2			.1.3.6.1.4.1.29133.11.3.7.0: Administrator SRV3 connected:							
Commu	nity put	blic	1	Severity	Clear			1				
5	Start	Stop		Entity	10.10.12			1				
000	Traps	: 4 Inform : 0		RemotePort	161							
				LocalPort	162							
				Community	public							
				Node	10.10.12							
				Source	10.10.12							
				TimeReceived	Mon Jun 20 02:22:43 VET 2022							
				HelpURL	0-0.html							
						_						

6.9 VC-MDx Administrator : disconnected

{.1.3.6.1.4.1. 29133.11.3.7} - VC-MDx Administrator : disconnected

🔨 Trap	Viewer					
Class	Туре	Source	Date	Message		
Clear	v2c Trap	10.10.10.12	Mon Jun 20 02:23:30 V	ET 2022.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 2		
Clear	v2c Trap	10.10.10.12	Mon 1 Kap Detai	s	-	х
			TimeStamp Enterprise	0 hours, 27 minutes, 52 seconds.		
			Generic Type			
Authe	enticate v1/ enticate v3	V2c traps (Comm Trap	Specific Type Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 27 minutes, 52 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.18: .1.3.6.1.4.1.29133.11.3.7.0: Administrator SRV3 disconnected:		
Port	162					
Commun	nity publ	lic	1 Severity	Clear		
S	tart	Stop	Entity	10.10.10.12		
000	Traps :	2 Inform : 0	RemotePort	161		
			LocalPort	162		
			Community	public		
			Node	10.10.10.12		
			Source	10.10.12		
			TimeReceived	Mon Jun 20 02:23:30 VET 2022		
			HelpURL	0-0.html		

SNMP V2

6.10 Channels inactivity (Restored Channel)

{.1.3.6.1.4.1. 29133.11.2.7} - Channels inactivity (Restored Channel)



🐔 Tra	apViewer			_		🙆 Trap Details	-	- 0	×
Class	Туре	Source	Date	Message		TimeStamp	1 hours, 7 minutes, 9 seconds.		
Clear	v3 Trap	10.10.10.12	Thu Oct 28 10:49:35 ICT 2021 Thu Oct 28 10:55:30 ICT 2021	. 1.3.6.1.2.1.1.3.0: TimeTick . 1.3.6.1.2.1.1.3.0: TimeTick	s: 0 hours, 4 s: 0 hours, 5	Enterprise			
Clear	v3 Trap	10.10.10.12	Thu Oct 28 10:59:07 ICT 2021	.1.3.6.1.2.1.1.3.0: TimeTick	s: 0 hours, 5				
Clear	v3 Trap	10.10.10.12	Thu Oct 28 10:59:26 ICT 2021	. 1.3.6.1.2.1.1.3.0: TimeTick	s: 0 hours, 5	Generic Type			
Clear	v3 Irap	10.10.10.12	Thu Oct 28 11:00:17 ICT 2021	1.3.6.1.2.1.1.3.0: TimeTick	s: U nours, 5				
Clear	v3 Trap	10.10.10.12	The Oct 28 11:00:18 ICT 2021	1.2.6.1.2.1.1.2.0; TimeTick	s: 0 hours, 5	Specific Type			
Clear	v3 Tran	10.10.10.12	Thu Oct 28 11:05:19 ICT 2021	1.3.6.1.2.1.1.3.0: TimeTick	s: 1 hours, 3				
Clear	v3 Trap	10.10.10.12	Thu Oct 28 11:09:07 ICT 2021	.1.3.6.1.2.1.1.3.0: TimeTick	s: 1 hours, 7 v	Message	.1.3.6.1.2.1.1.3.0: TimeTicks: 1 hours, 7 minutes, 9 seconds.:		
							.1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.7		
🖂 Au	thenticate	e v1/v2c traps (Con	nmunity)	Enable Logging	Log Format 🗸		.iso.org.dod.internet.private.enterprises.atis.vcRecorder.record	erData.	record
							erChannelInactivity.0: The activity was restored on channel 28:		
Au 🖂	thenticate	e v3 Trap		Enable Mail C	Configure Mail				
Port		162	TrapList 162	public 🗸 Add	Del	Severity	Clear		_
Comm	unity	public	TrapParser 10.1	0.10.12	Load				
	Start	Stop	Show Details	Delete Entry	ParserEditor	Entity	10.10.10.12		
			0			RemotePort	161		
	• Irap	s: 11 inform: 0	Status	: Listening for Traps					
						LocalPort	162		
						Community	null		
						Node	10.10.10.12		
						Source	10.10.12		
						TimeReceived	Thu Oct 28 11:09:07 ICT 2021		
						HelpURL	0-0.html		

6.11 Recording started/stopped event (Stopped Channel)

{.1.3.6.1.4.1. 29133.11.3.14} - Recording started/stopped event (Stopped Channel)

SR 🔛	V3 - VC-MDx	Recorder - IR Buffe	er Records - Supe	r										- 0	×
<u>L</u> ock	<u>V</u> iew <u>R</u> e	cords <u>S</u> ettings	<u>S</u> ervice <u>I</u>	<u>H</u> elp											
	73	2		<u> </u>		a 😹 🍘							7: 1	9:59	5
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca Marked	Direction	Start Time	Stop Time	Duration	Disc Lab	
Clos	ed 4981	5	Analog				No		No		17/06/2022 3:04:04	17/06/2022 3:05:55	00:01:51		
Clos	ed 4980	3	Analog				No		No		17/06/2022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS 202	
Clos	ed 4979	3	Analog				No		No		17/06/2022 2:28:30	17/06/2022 2:28:46	00:00:16		
Close	ed 4978	1	Analog				No		Yes		17/06/2022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS 202	
Clos	ed 4977	3	channel_3				No		No		17/06/2022 1:57:19	17/06/2022 2:00:22	00:03:02		America
Clos	ed 4976	1	channel_1				No		Yes		17/06/2022 1:54:44	17/06/2022 1:55:11	00:00:27		- 4
Close	ed 4975	1	channel_1				No		Yes		17/06/2022 1:53:22	17/06/2022 1:54:18	00:00:56		
De Clos	ed 4974	2	channel_2				No		Yes		16/06/2022 6:32:13	16/06/2022 6:32:29	00:00:16		A lower
Clos	ed 4973	1	channel_1				No		Yes		16/06/2022 6:28:58	16/06/2022 6:29:53	00:00:55		
Clos	ed 4972	1	channel_1				No		Yes		16/06/2022 6:01:40	16/06/2022 6:02:06	00:00:26		
P Clos	ed 4971	2	channel_2				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		
Clos	ed 4970	1	channel_1				No		No		14/06/2022 10:10:39	14/06/2022 10:11:00	00:00:21		Te-
P Clos	ed 4964	2	channel_2				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
Clos	ed 4963	1	channel_1				No		No		14/06/2022 6:16:52	14/06/2022 6:16:59	00:00:07		
P Clos	ed 4969	2	channel_2			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		
Clos	ed 4968	1	channel_1			13/06	No		No		13/06/2022 6:50:45	13/06/2022 6:51:18	00:00:33		1.1
Clos	ed 4967	5	channel_5				No		No		13/06/2022 6:48:23	13/06/2022 6:48:33	00:00:10		manuel of
P Clos	ed 4966	2	channel_2				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00:00:18		Ta-IV
Clos	ed 4965	1	channel_1				No		No		13/06/2022 6:22:14	13/06/2022 6:22:31	00:00:18		
															J.J. James
															100 X
<														>	
Displa	ved records:	19 (1 - 19) / Filtered	: 19/Total: 19												
Start ti Stop ti Directi Record	me: me: on: 1 ID:		Calling No.: Called No.: Compressio DSE:	arc .						Loop					5
Short (Comment:		Save	Comment					Vo	lume B	ack offset Duratio 10 📰 (s) 60 =	(s) Flexi	Skip 5 📩 (s) <mark>5</mark>	: ::::::::::::::::::::::::::::::::::::
Re	cording Chan	nels	Record	ing Channels		= 🗊 🕞 C	onnected to 0 c	of 1 VOIP ser	/er(s)						
(iii)	Active Calls: 0		1	2	3	4 5	6	7	8	9	10 11	12 13	1	4	^
	2584-25					J 🚛			4	1	/ ×	a 🚛	S /		
IR	Buffer		Analog	Analog	Analog	Analog Analog	Analog	Analog	Analog	Analog	Analog Analog	Analog Anal	og Ana	alog	
III F	rom: 13/06/20	22 6:22:14	15	16	17	18 19	20	21	22	23	24 25	26 27	2	8	
+11	o: 17/06/20	22 3:05:55		1	12		N	<u> </u>	12	12	12 12		1	1	
De	cks		Analog	Analog	PCM	PCM PCM	PCM	PCM	PCM	PCM	PCM PCM	PCM PCI	I PC	M	
01	AS Ready U	sed 0%	20	30	31	32 22	24	25	36	37	38 20	40 41		2	
01	Ejected		23	50		JZ 33		30			- 30 - 30 	40 41		-	
-			- 1		4	4	4			4	Las Las		4		
Me	ssages		PCM	PCM	PCM	PCM PCM	PCM	PCM	PCM	PCM	PCM PCM	PCM PCI	л РС	-m	~
	lew messages Errors: 0, ∧∿W	s: 0 arnings: 0		Start All	a	top All	💉 Configurat	ion	Advanced Show all c	channel info	rmation				

🔍 Trap	Viewer				- • ×
Class	Туре	Source	Date		Message
Clear	v2c Trap	10.10.10.12	Mon Jun 2	20 02:05:02 VET 202	2.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 9
				🅌 Trap Details	-
				TimeStamp [Enterprise	0 hours, 9 minutes, 24 seconds.
				Generic Type	
Autho	enticate v enticate v	1N2c traps (Commi 3 Trap	unity)	Specific Type	.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 9 minutes, 24 seconds.: .1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.20: .1.3.6.1.4.1.29133.11.3.14.0: Recording stopped:
Port	16	2	Tr		8 55
Commun	nity pul	olic	Trap	Severity	Clear
S	Start	Stop	S	Entity	10.10.12
000	Traps	: 1 Inform : 0		RemotePort	161
				LocalPort	162
				Community [public
				Node	10.10.12
				Source	10.10.12
				TimeReceived	Mon Jun 20 02:05:02 VET 2022
				HelpURL	0-0.html

6.12 Recording started/stopped event (Started Channel)

{.1.3.6.1.4.1. 29133.11.3.15} – Recording started/stopped event (Started Channel)

SRV3	- VC-MDx R	ecorder - IR Buffe	r Records - Supe	r										- C) X
Lock }	jew <u>R</u> eco	ords <u>S</u> ettings	Service H	Help			_								
13	73	2				SNMP	2						-1:2	33	
Status	Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca Marked	Direction	Start Time	Stop Time	Duration	Disc ^	
& Active	4997	16	Analog				No		No		17/06/2022 7:21:42				
Active	4996	15	Analog				No		No		17/06/2022 7:21:42				
Active	4995	14	Analog				No		No		17/06/2022 7:21:42				
Active	4994	13	Analog				No		No		17/06/2022 7:21:42				
& Active	4993	12	Analog				No		No		17/06/2022 7:21:42				America
Active	4992	11	Analog				No		No		17/06/2022 7:21:42				
Active	4991	10	Analog				No		No		17/06/2022 7:21:42				
Active	4990	9	Analog				No		No		17/06/2022 7:21:42				A
& Active	4989	8	Analog				No		No		17/06/2022 7:21:42				10
Active	4988	7	Analog				No		No		17/06/2022 7:21:42				
Active	4987	6	Analog				No		No		17/06/2022 7:21:42				
Active	4986	5	Analog				No		No		17/06/2022 7:21:42				Te-
& Active	4985	4	Analog				No		No		17/06/2022 7:21:42				
Active	4984	3	Analog				No		No		17/06/2022 7:21:42				
Active	4983	2	Analog				No		Yes		17/06/2022 7:21:42				
Active	4982	1	Analog				No		Yes		17/06/2022 7:21:42				1.1.1
Closed	4981	5	Analog				No		No		17/06/2022 3:04:04	17/06/2022 3:05:55	00:01:51		To Joseph
Closed	4980	3	Analog				No		No		17/06/2022 2:29:13	17/06/2022 2:29:33	00:00:20	NAS	
Closed	4979	3	Analog				No		No		17/06/2022 2:28:30	17/06/2022 2:28:46	00:00:16		
Closed	4978	1	Analog				No		Yes		17/06/2022 2:23:21	17/06/2022 2:24:18	00:00:57	NAS	The second
Closed	4977	3	channel 3				No		No		17/06/2022 1:57:19	17/06/2022 2:00:22	00:03:02	~	10-1V
C1-41			C-11							_oop					
Starttime			Calling No.:												5
Stop time			Called No.:												
Direction			Compressio	n:										1 60	
Record II			DSE:							44 1			· · · · · ·		
			_	100					Vol	ume Bi	ack offset Duratio	Elevi	Skip	DS	E
Short Co	mment:		Save	Comment							10 🗮 🕲 🛛 60 🗄		5 🗮 (s) 5	📑 (s)
Reco	rding Channe	łs	Record	ing Channels		-00-	Connected to 0 (of 1 VOIP ser	ver(s)						
Sal Act	ive Calls: 16		1	2	3	4 5	6	7	8	9	10 11	12 1	3 1	14	^
			1 60	10 m	N	r (H	1	No	2	643		R 61	3	5	
ID D.			Analog	Analog	Analog A	nalog Analo	Analog	Analog	Analog	Analog	Analog Analog	Analog Ana	log An	alon	
IN DU	12/00/2020	0.00.14	15	10	17	10 10	20	01	22	00	24 25	20 2		10	
HI To:	17/06/2022	3.05.55	15	0		10 13	20	21	11	25	24 25	20 2		10	
				4	L L		2	2	1	115	44 44	1 1	A U	1	
Deck	5		Analog	Analog	PCM I	PCM PCM	PCM	PCM	PCM	PCM	PCM PCM	PCM PC	M PC	ZM	
@NA	S: Ready, Use	d 0%	29	30	31	32 33	34	35	36	37	38 39	40 4	1 4	12	
At	ected			11	1 1			41	11	11	ar ar		3 4		
Mess	ages		PCM	PCM	PCM	PCM PCM	PCM	PCM	PCM	PCM	PCM PCM	PCM PC	.м РС	SM	~
€3Nev Merro	v messages: 1 ors: 0, A+Wan	2 nings: 0		a Start All	😰 Stop	All	Configurat	ion)	Advanced	channel infor	mation				
									Onlow dir c						

					🌆 Trap Details		×
🍕 TrapViewe	8				TimeStamp	1 hours, 6 minutes, 37 seconds.	
Class	Туре	Source	Date				
Clear	v2c Trap	10.10.10.1	2 Mon Jur	n 20 03:01:16	Enterprise		
Clear	v2c Trap	10.10.10.1	2 Mon Jur	20 03:01:17			
Clear	v2c Trap	10.10.10.1	2 Mon Jur	n 20 03:01:18	Constant Trans		
Clear	v2c Trap	10.10.10.1	.2 Mon Jur	1 20 03:02:15	Generic Type		
Clear	v2c Trap	10.10.10.1	.2 Mon Jur	1 20 03:02:16			
Clear	v2c Trap	10.10.10.1	.2 Mon Jur	n 20 03:02:17	Specific Type		
					Message	136121130. TimeTicke: 1 hours 6 minutes 37 seconds .	
						13616311410. Object TD: 13614129133112021.	
🗹 Authentica	e v1/v2c traps (Commu	inity)		Enable Loggi	r	.1.3.6.1.4.1.29133.11.3.15.0: 16 records in last interval:	
Authentica	e v3 Trap			Enable Mail			
Port	162	TrapList	162:public	✓ Ad	Severity	Clear	
Community	public	TrapParser	10.10.10.12		Entity	10.10.10.12	
Start	Stop	Show Detail	ls De	lete Entry			
Tr	aps : 6 Inform : 0	S	Status : Lister	ing for Traps	RemotePort	161	
					LocalPort	162	
					Community	public	
					Node	10.10.10.12	
					Source	10.10.12	
					TimeReceived	Mon Jun 20 03:02:15 VET 2022	
					HelpURL	0-0.html	

6.13 Network client connected/disconnected (VDS Sip Passive service started)

 $\{.1.3.6.1.4.1. 29133.11.3.21\}$ – Network client connected/disconnected (VDS Sip Passive service started)

7 3			· 👌 I	0	L 😹 🕜			-					EF	5:51	5
Is Record ID	Channel Num	Channel Name	User ID	Case	Short Comment	Protected	Called N	Ca	Marked	Direction	Start Time	Stop Time	Duration	Disc ^	
osed 4997	16	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4996	15	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4995	14	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4994	13	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4993	12	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	A DESCRIPTION
osed 4992	11	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4991	10	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4990	9	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	America
osed 4989	8	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	12 M
osed 4988	7	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4987	6	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	-
osed 4986	5	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	10-1
osed 4985	4	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4984	3	Analog				No			No		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4983	2	Analog				No			Yes		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4982	1	Analog				No			Yes		17/06/2022 7:21:42	17/06/2022 7:25:5	00:04:16	NAS	
osed 4981	5	Analog				No			No		17/06/2022 3:04:04	17/06/2022 3:05:5	00:01:51		The state
osed 4980	3	Analog				No			No		17/06/2022 2:29:13	17/06/2022 2:29:3	00:00:20	NAS	
osed 4979	3	Analog				No			No		17/06/2022 2:28:30	17/06/2022 2:28:4	00:00:16		
osed 4978	1	Analog				No			Yes		17/06/2022 2:23:21	17/06/2022 2:24:1	00:00:57	NAS	
osed 4977	3	channel_3				No			No		17/06/2022 1:57:19	17/06/2022 2:00:2	00:03:02	~	inimizator.
t time:		Calling No.:								oop					
time:		Called No.:													
ction:		Compressio	m:						-						
ord ID:		DSE:								44 1			X	1 2	9
rt Comment.		Save	Comment)					Vol	ume B.	ack offset Duratio	n Flexi	Skip 5 🚞 (DS s) <u>5</u>	E 🛨 (s)
Recording Chan	iels	Message	5												
Metive Calls: 0		Message										Ack	nowledged		
			/2022 7:35:15	10.10.10.12 VDS co	nnected							NO			
R Buffer From: 13/06/20 To: 17/06/20	22 6 22 14 22 7 25 58														
Decks	ed 0%														
Decks NAS: Ready, U: A: Ejected															

💐 Trap	Viewer				— — ×							
Class	Туре	Source	Date		Message							
Clear	v2c Trap	10.10.10.12	Mon Jun	20 02:15:03 VET 20	22.1.3.6.1.2.1.1.3.0: TimeTicks: 0 hours, 1							
Clear	v2c Trap	10.10.10.12	Mon Jun	🙆 Tran Detaile								
Clear	v2c Trap	10.10.10.12	Mon Jun	In the Decails			~					
Quear Auth	enticate v1/	10.10.10.12	nunity)	TimeStamp Enterprise Generic Type Specific Type Message	0 hours, 19 minutes, 34 seconds.							
Auth	enticate v3	Trap			.1.3.6.1.6.3.1.1.4.1.0: Object ID: .1.3.6.1.4.1.29133.11.2.0.18:							
2233	1000				.1.3.6.1.4.1.29133.11.3.21.0: VDS Server 10.10.10.12 connected:							
Port	162		10		.1.3.6.1.4.1.29133.11.3.23.0: INTEGER: 1:							
Commu	nity publ	ic	Trap	Severity								
Ş	Start	Stop	S		Ciear							
	Trane	4 Inform : 0		Entity	10.10.12							
	Traps.	4 11101111. 0	_	RemotePort	161							
				LocalPort	162							
				Community	public							
				Node	10.10.12							
				Source	10.10.12							
				TimeReceived	Mon Jun 20 02:15:12 VET 2022							
				HelpURL	0-0.html							

System warnings (VDS Sip Passive service stopped) 6.14

{.1.3.6.1.4.1. 29133.11.3.21} - System warnings (VDS Sip Passive service stopped)

SRV3 -	VC-MDx Rec	order - IR Buffe	Records - Super								- [X	
Lock Vie	w <u>R</u> ecord	ds <u>S</u> ettings	<u>S</u> ervice <u>H</u> elp										
	3	5	📕 (B) 👌		😹 🕜)				7:4	- :	5	
Status	Record ID 0	Channel Num	Channel Name User	ID Case	Short Comment	Protected	Called N Ca Marked	Direction Start Time	Stop Time	Duration	Disc ^		1
Closed 4	4997	16	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed 4	4996	15	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed 4	4995	14	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed	4994	13	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	MAS		
Closed	4992	11	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed	4991	10	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed 4	4990 9)	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS	A Design	
Closed 4	4989 8	3	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS	12-12-	
Closed 4	4988	7	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed 4	4987 6	5	Analog			No	No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS	1999 - C	
Closed	4986 3		Analog			No	No	17/06/2022 7:21:4	2 1//06/2022 /:25:58	00:04:16	NAS		
Closed	4985 4	1	Analog			No	No No	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed 4	4002	2	Analog			No	Yee	17/06/2022 7.21.4	2 17/06/2022 7.25.56	00-04-16	NAS		
Closed	1982		Analog			No	Yes	17/06/2022 7:21:4	2 17/06/2022 7:25:58	00:04:16	NAS		
Closed	4981	5	Analog			No	No	17/06/2022 3:04:0	4 17/06/2022 3:05:55	00:01:51	10.10	interest (1)	
Closed 4	4980	3	Analog			No	No	17/06/2022 2:29:1	3 17/06/2022 2:29:33	00:00:20	NAS		
Closed 4	4979 3	3	Analog			No	No	17/06/2022 2:28:3	0 17/06/2022 2:28:46	00:00:16			
Closed 4	4978	l I	Analog			No	Yes	17/06/2022 2:23:2	1 17/06/2022 2:24:18	00:00:57	NAS		
Closed 4	4977 3	3	channel_3			No	No	17/06/2022 1:57:1	9 17/06/2022 2:00:22	00:03:02	~	10-1-	
۲.											>	_	
Displayed	records: 35 (1 - 35) / Filtered:	35 / Total: 35										
							-	Loop					
Start time:			Calling No.:				(C)				_		
Stop time:			Called No.:										
Direction:			Compression:					44	N NO D	· · · · · ·	1.6	(N)	
Record ID:			DSE:				Vo	lume Pack offert Dura	ution	Skin	n	SE	
Short Com	ment		Save Comm	ent					(s) Flexi			(1)	
Contraction of the													
										3			1
			Messages			_				3			
Record	ling Channels		Messages							3 (
Record Activ	ling Channels e Calls: 0		Messages Message						Ackni	owledged			
Record Sill Active	ling Channels e Calls: 0		Messages Message 17/06/2022 7	37:34 10.10.10.12 VDS	disconnected				Ackni	owledged			
Record Să Activ	ling Channels e Calls: 0 er		Messages Message 17/06/2022 7 17/06/2022 7	:37:34 10.10.10.12 VDS :35:15 10.10.10.12 VDS	disconnected connected		2.0111		Ackni NO NO	owledged			
Record	ting Channels e Calls: 0 er : 13/06/2022 6	:22:14	Messages Message \$17/06/2022 7 \$17/06/2022 7	:37:34 10.10.10.12 VDS :35:15 10.10.10.12 VDS	disconnected connected		2000		Ackm NO NO	owledged			
Record Sill Active IR Buffi I* From #I To:	ting Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7	:22:14 :25:58	Messages Message S 17/06/2022 7 17/06/2022 7	:37:34 10.10.10.12 VDS :35:15 10.10.10.12 VDS	disconnected connected				Ackn NO NO	wiedged			
Record Sta Active IR Buffi III From 41 To: Decks	ling Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7	:22:14 :25:58	Messages Message 17/06/2022 7	37:34 10 10.10 12 VDS 35:15 10.10.10.12 VDS	disconnected connected				Ackni NO NO	wiedged			
Record Star Activ IR Buffi II: From II: From II: To: Decks	ling Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used	:22:14 :25:58 0%	Messages Message 17/06/2022 7	37:34 10.10.10.12 VDS 35:15 10.10.10.12 VDS	disconnected connected				Action NO NO	wiedged			
Record Star Active IR Buffi III: From 41 To: Decks © NAS; Ø A: Eje	Fing Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used ected	:22:14 :25:58 0%	Message Message \$17/06/2022 7 \$17/06/2022 7	37:34 10.10.10.12 VDS 35:15 10.10.10.12 VDS	deconnected connected				Ackini NO NO	wiedged			
Record Active IR Buffi I* From *I To: Decks @ NAS: @ A: Eje Messag	ting Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used scted ges	:22:14 :25:58 0%	Messages Message ⊗ 17/06/2022 7 ↓ 17/06/2022 7	37:34 10.10.10.12 VDS 35:15 10.10.10.12 VDS	deconnected connected				Ackin NO NO	wiedged			
Record Active IR Buffi III From III From III From III From III Suffi III From III Suffi III Suffi I	ting Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used scted pes messages: 2	:22:14 :25:58 0%	Messages Message ♀ 117/06/2022 7 ♀ 117/06/2022 7	37:34 10.10.10.12 VDS 35:15 10.10.10.12 VDS	deconnected connected	Delete	Delete All		Aekm NO NO	s wiedged			
Record Si Active IR Buffi II: From II: From II: From II: From II: From II: From II: From II: Source A: Eje Messag Si New A: Error	ting Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used scted ges messages: 2 s: 1, /s-Warnin	:22:14 :25:58 0%	Messages Message ↑ 17/06/2022 7 ↓ 17/06/2022 7	37.34 10.10 10.12 VDS 35.15 10.10 10.12 VDS	deconnected connected	Delete	Delete All		Action NO NO	wledged			
Recore Sta Activ IR Buffi IF From 41 To: Decks Ø NAS: Ø A: Ejt Messag Callew Ar Error	ting Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used exted ges messages: 2 s: 1, AsWarnin	:22:14 :25:58 0% ngs: 0	Messages Message ♀ 17/6/2022 7 ♀ 17/6/2022 7 ♀ 17/6/2022 7	37.34 10.10 10.12 VDS 35.15 10.10 10.12 VDS	deconnected connected ledge All	Delete) X Delete All		Action NO NO	wiedged			
Recorr Sta Activ IR Buff IF From 41 To: Decks © NAS: © NAS: © NAS: © NAS: © NAS: © NAS: © NAS: © A: Ejt Messag	ting Channels e Calls: 0 er : 13/06/2022 7 17/06/2022 7 Ready, Used scted ges messages: 2 s: 1, //e-Warnin	:22:14 :25:58 0% ngs: 0	Messages Message ● 17/06/2022 7 ↓ 17/06/2022 7 ↓ 17/06/2022 7	37:34 10. 10. 10. 12 VDS 35:15 10 10 10. 12 VDS ;e ✓ Acknow	deconnected connected ledge All	Delete) X Delete All		Actent NO NO	wiedged			
Recorr Sta Activ IR Buff IF From 41 To: Decks © NAS: © A: Ejt Messag Callew A Error	ting Channels e Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used scted ges messages: 2 s: 1, //s-Warnis	-22-14 -25-58 0% 	Messages Message ● 17/06/2022 7 ↓ 17/06/2022 7 ↓ 17/06/2022 7	37.34 10 10 10 12 VDS 35.15 10 10 10 12 VDS je ✔ Acknow	deconnected connected ledge All	Delete) Delete All		Ackini NO NO	wledged			
Record Sta Activ IR Buff # From # To: Decks @ A: Epr Messag SJNew # Error	Ing Channels e Calls: 0 er 13106/2022 6 17106/2022 7 Ready, Used scted ges messages: 2 s: 1, A=Warnin Viewer	122-14 225-58 0%	Messages Message ↑776/2022 7 ↓1776/2022 7 ↓1776/2022 7 ↓Acknowled;	37.54 10.10.12 VDS 35.15 10.10.10.12 VDS	deconnected connected ledge All	Delete) X Delete All		Action NO NO	wledged			
Record State Active IR Buff # From # To: Decks @ A: Ept Messag Sulvew # Error	Ing Channels c Calls: 0 er : 13/06/2022 6 17/06/2022 7 Ready, Used scted ges messages: 2 s: 1, A-Warnin Viewer	122-14 25:58 0% 199: 0	Messages Message ● 17/05/2022 7 ↓ 17/05/2022 7 ↓ 17/06/2022 7	37:54 10 10 10 12 VDS 35:15 10 10 10 12 VDS ;e	deconnected connected ledge All	Delete) X Delete All		Actorn NO NO	wledged			
Record Stateday IR Buffi IR Buffi IR Buffi IF From A: Error Class Class	ing Channels e Calls: 0 er : 13/06/2022 6 Ready, Used scted ges messages: 2 s: 1, A=Warnin Viewer Type	22-14 25:58 0% ngs: 0	Messages Message ● 17/66/2022 7 ↓ 17/06/2022 7 ↓ 17/06/2022 7 ↓ 4 Acknowledge Date Date	37:34 10.10.10.12 VDS 35:15 10.10.10.12 VDS ;e	deconnected connected ledge All XC	Delete) Delete All X		Action NO NO	wiedged			
Record Statute IR Buff IF Buff IF From IF From To Decks © NAS: © A: Ein Messag Calles Class Class Class Class	Img Channels c Calls: 0 er : 13/06/2022 6 : 13/06/2022 7 Ready, Used sted ses : 1, AsWamin Viewer Type v2c Trap v2c Trap	22:14 25:58 0% sgs: 0	Messages Message ↑ 7/06/2022 7 ↓ 17/06/2022 7 ↓ 17/06/202 ↓ 17/06/200 ↓ 17/06/200 ↓ 17/06/200 ↓ 17/00	37:34 10 10 10 12 VDS 35:15 10 10 10 12 VDS je	deconnected connected ledge All	Delete	Delete All		Ackini	wiedged			×
Record Statute IR Buffi # Trom # Tro: Decks @ NAS: @ NAS: @ NAS: @ NAS: @ NAS: @ NAS: @ Trap Class Clear Clear	Img Channels c Calls: 0 er 11/06/2022 6 T1/06/2022 7 Ready, Used sched yes messages: 2 s: 1, As Warnis Viewer Type v2c Trap v2c Trap v2c Trap	22-14 25:58 0% sge: 0	Message Message ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 17/6/2022 7 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12	37:54 10:10:12:VDS 35:15:10:10:10:12:VDS ;e	deconnected connected ledge All	Delete) Delete All		Actorn NO NO	wiedged			×
Record Sa Activ IR Buffi IIR Buffi I	ing Channels c e Calls: 0 r ri 13/06/2022 f i 13/06/2022 f ges ressages: 2 ri 1, A-Warning	22-14 25-58 0% Source 10.10.10 10.10.10 10.10.10 10.10.10	Message Message ● 17/06/2022 7 ● 11/06/2022 7 ● 11/06/2022 7 ● 000 00000000000000000000000000000000	37.34 10.10.12.12 VDS 35.15 10.10.10.12 VDS ie	deconnected connected ledge All XC	Delete	29 seconds		Action NO NO	wiedged	1.5		×
Record States IR Buff IF From IF From To Decks In A Ege Message Caller Class Clear Clear Clear Clear	ing Channels e Calls: 0 er : 13/06/2022 6 : 13/06/2022 7 Resdy, Used scted Viewer Type v2c Trap	22:14 (25:58 0% source 10,10,10 10,10,10 10,10,10 10,10,10 10,10,10	Message Message ↓ 17/06/2022 7 ↓ 17/06/202 7 <	37.34 10 10 10 12 VDS 35.15 10 10 10 12 VDS ie	deconnected connected ledge All X ssage c 0 hours, 20 m	Delete	X Delete All X 29 seconds.		Action NO NO	wiedged			×
Record SA Activ IR Buff IN From # To: Decks @ A2 Eyr @ A2 Eyr Messag Class Clear Clear Clear Clear Clear Clear	Iing Channels Calls: 0 er :13/06/2022 6 17/06/2022 7 Ready, Used scied ps messages: 2 ss: 1, /a×Warnis Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap	22:14 25:58 0% 99:0 Source 10,10,10 10.10,10 10.10,10 10.10,10 10.10,10	Message Message ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 11/06/2022 7 ■ 11/06/2022 7 ■ 11/06/2022 7 ■ 11/06/2022 7 ■ 11/06/2022 7 ■ 11/06/2022 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/202 7 ■ 11/06/2	37.34 10.10.10.12 VDS 35.15 10.10.10.12 VDS set	deconnected connected ledge All XC ssage : 0 hours, 20 m	Delete	X Delete All X 29 seconds.		Action NO NO	swiedged	1		×
Record Sta Activ IR Buff In From October Of Activ Acti	Img Channels e Calls: 0 er :13/06/2022 6 17/06/2022 7 Ready, Used scted :1, /s-Warnin Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap	22:14 25:58 0% Source 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10	Message Message ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 0 10/06/2002 7	37:34 10 10 10 12 VDS 35:15 10 10 10 12 VDS 35:15 10 10 10 12 VDS (deconnected connected ledge All XC ssage c hours, 20 m	Defete	X Delete All X 29 seconds.		Acian	wiedged	× 100		×
Record States IR Buffi IF From To Decks On AS: A Error Massa Callear Clear Clear Clear Clear Clear Clear	Fing Channels c Calls: 0 er 13/06/2022 6 17/06/2022 7 17/06/2022 7 messages: 2 2 messages: 2 : 1, #>Warnin Viewer Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap	22-14 25:58 0% 50urce 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10	Message Message ● 17/66/2022 7 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 12 ● 13/10 10 20 02 ■ 12 ● 13/10 10 20 02	37:54 10:10:12:VDS 35:15:10:10:10:12:VDS ie	deconnected connected ledge All X ssage i 0 hours, 20 m	Delete	X Delete All X 29 seconds.		Actorn NO NO	swiedged			×
Record State IR Buff From 4 To: Decks O NAS: O Class Class Class Clear Clear Clear Clear	Fing Channels Calls: 0 er :1306/2022 6 :1706/2022 7 17/06/2022 7 Ready, Used Used pressages: 2 :1, /s/Warnis Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap	22:14 25:58 0% 99:0 50urce 10,10,10 10,10,10 10,10,10 10,10,10 10,10,10 10,10,10	Message Message ↓ 17/6/2027 ↓ 17/6/20 ↓ 17/6/20 ↓ 17/6/20 ↓ 17/6/20 ↓ 17/6/20 ↓ 17/6/20 ↓ 17/6/20	37.34 10.10.10.12 VDS 35.15 10.10.10.12 VDS 35.15 10.10.10.12 VDS	deconnected connected Hedge All XC Issage	Delete	Delete All X Delete All X 29 seconds.		Action NO NO	swiedged			×
Record State IR Buff IF From Octos O AAS O AAS O AAS Cass Clear Clear Clear Clear Clear	Img Channels e Calls: 0 er :13/06/2022 6 17/06/2022 7 Ready, Used scted :1, /s-Warnin Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap	22:14 25:58 0% Source 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10	Message Message ● 17/06/2022 7 ● 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0 ■ 0	37.34 10.10.12.12 VDS 35.15 10.10.10.12 VDS 35.15 10.10.10.12 VDS	deconnected connected ledge All XC ssage c b hours, 20 m	Defete	X Delete All X 29 seconds.			swiedged			×
Record Sta Activ IR Buff IF From To Decks O Activ A Error Clear Clear Clear Clear Clear Clear	Fing Channels c Calls: 0 er 13/06/2022 6 17/06/2022 7 17/06/2022 7 Ready, Used acted seasages: 2 wessages: 2 :: 1, #>Warnin Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap	22-14 25-58 0% Source 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10	Message Message 17/06/2022 7 ↓ 17/06/202 7 <td< td=""><td>37.54 10.10.12.VDS 35.15 10.10.10.12.VDS 35.15 10.10.10.12.VDS ie ✓ Acknow Mi Trap Detail 11 11 11 11 11 11 11 11 11 11 11 11 11</td><td>deconnected connected ledge All X ssage ; 0 hours, 20 m .1.3.6.1.2.1.</td><td>Delete</td><td>Z9 seconds.</td><td>ours, 20 minutes,</td><td>Adam NO NO 29 seconds.:</td><td>swiedged</td><td></td><td></td><td>×</td></td<>	37.54 10.10.12.VDS 35.15 10.10.10.12.VDS 35.15 10.10.10.12.VDS ie ✓ Acknow Mi Trap Detail 11 11 11 11 11 11 11 11 11 11 11 11 11	deconnected connected ledge All X ssage ; 0 hours, 20 m .1.3.6.1.2.1.	Delete	Z9 seconds.	ours, 20 minutes,	Adam NO NO 29 seconds.:	swiedged			×
Record State IR Buff From To Class Class Clear	Type Press Yes Yz Yz Yz	22:14 25:58 0% 10:10:10:10 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10 10:10:10	Message Message 17/06/2022 7 ↓ 17/06/202 7 ↓ 17/06/202 7 ↓ 17/06/202 7 ↓ 10/10 10 10 20 2 ↓ 10/10 10 10 20 2	a7:34 10.10.12.VDS 35:15 10.10.10.12.VDS 35:15 10.10.10.12.VDS	deconnected connected ledge All XC ssage 0 hours, 20 m 	Delete	Z9 seconds.	ours, 20 minutes, 1.3.6.1.4.1.291	29 seconds.: 33.11.2.0.12:	swiedged			×
Record State IR Buff IF From # To: Decks @ A. Er Sullew # Error Clear Clear Clear Clear Clear Clear Clear Clear	imag Charmels e Calls: 0 er ::1306/2022 6 if :1706/2022 7 Resdy, Used :1706/2022 7 penessages: 2, :1, /s-Warnin :1706/2022 7 Viewer :1709 Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap vac Trap v2c Trap vac Trap v2c Trap	22:14 25:58 0% Source 10:10:10 10:10	Message Message ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 0 ate 12 Mon Jun 20 02 12 Mon Jun 20 02 ■ 0 mmunity)	a7.34 10 10 10 12 VDS 35.15 10 10 10 12 VDS 35.15 10 10 10 12 VDS	deconnected connected ledge All X0 ssage : 0 hours, 20 m 1.3.6.1.2.1. 1.3.6.1.4.1.	Delete	Z9 seconds.	ours, 20 minutes, 	29 seconds.: 33.11.2.0.12: VDS	discon	necte		×
Record State Activ IR Buffi IF From To Decks On AS: On AS:	Fing Channels Calls: 0 er 13/06/2022 6 17/06/2022 7 17/06/2022 7 Ready, Used sched Seanses; 2 messages; 2 s: 1, 49-Warnin Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap enticate v1/ enticate v3	22-14 25-58 0% 50urce 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10 10.10.10	Message Message ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ● 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 17/06/2022 7 ■ 11/2 Mon Jun 20 02	37.54 10.10.12.VDS 35.15 10.10.10.12.VDS 35.15 10.10.10.12.VDS 40 40 40 40 40 40 40 40 40 40	deconnected connected ledge All X ssage j 0 hours, 20 m 1.3.6.1.2.1. 1.3.6.1.6.3. 1.3.6.1.4.1.	Delete	Z9 seconds. TimeTicks: 0 h .0: Object ID: 1.3.31.0: 20/06	ours, 20 minutes, .1.3.6.1.4.1.291 /2022 6: 46: 06 1	29 seconds.: 33.11.2.0.12: 0.10.10.12 VDS	discon	necte		×
Record State IR Buff IF From From Too Decks In Active Message Too New Ar Error Clear	Img Channels Callis: 0 er :13/06/2022 6 :17/06/2022 7 Ready, Used pressages: 2 ::::::::::::::::::::::::::::::::::::	22:14 25:58 0% 99:0 50urce 10,10,10 10,10 10,10 10,10,10,10 10,10,100 10,10,100 10,10,100 10,10,100,10	Message Message ↓ 17/6/2027 ↓ 17/6/2027	a7:34 10.10.12.12 VDS 35:15 10.10.10.12 VDS 35:15 10.10.10.12 VDS	deconnected connected Hedge All XC ssage	Delete	X Delete All X 29 seconds. TimeTicks: 1.3.31.0:	ours, 20 minutes, .1.3.6.1.4.1.291 /2022 6: 46: 06 1	29 seconds.: 33.11.2.0.12! 0.10.10.12 VDS	discon	uter interest interes		×
Record Sta Activ IR Buff IF Form * To: Decks @ A. Ek Messay & Error Clear	Image Charmeds Fer Fer 13/06/2022 6 T17/06/2022 7 Ready, Used Per messages: 2 remessages: 2 :: 1, /s-Warnin Viewer Type v2c Trap v2c Trap v2c Trap v2c Trap v2c Trap 12/2 Trap v2c Trap 162 enticate v3 162	22:14 25:58 0% Source 10:10:10 10:10	Message Message Image Im	a7 34 10 10 10 12 VDS 35 15 10 10 10 12 VDS 35 15 10 10 10 12 VDS Met 11 11 11 11 11 11 11 11 11 11 11 11 11	deconnected connected ledge All XC ssage ; 0 hours, 20 m	Delete	X Delete All X Delete All X 29 seconds. TimeTicks: 0 h .0: Object ID: 1.3.31.0: 20/06	ours, 20 minutes, .1.3.6.1.4.1.291 /2022 6: 46: 06 1	29 seconds.: 33.11.2.0.12: 0.10.10.12 VDS	discon	necte		×

Stop

Traps : 5 Inform : 0

Show D RemotePort

LocalPort

Community

Node

Source

HelpURL

161

162

public

10.10.10.12

10.10.10.12 TimeReceived Mon Jun 20 02:16:07 VET 2022

0-0.html